Release Notes for Cisco Catalyst IE3x00 and IE3100 Rugged, IE3400 Heavy Duty, and ESS3300 Series Switches, Cisco IOS XE Dublin 17.12.x

First Published: 2023-07-28

Last Modified: 2026-08-05

Introduction

This document provides release information for the following Catalyst IE and Cisco ESS switches:

- Cisco Catalyst Rugged Series Switches (IE3100, IE3105, IE3200, IE3300, and IE3400)
- Cisco Catalyst IE3400 Heavy-Duty Series (IE3400H)
- Cisco Embedded Services 3300 Series (ESS3300)

Cisco Catalyst IE3x00 Rugged Series Switches feature advanced, full Gigabit Ethernet speed for rich real-time data—and a modular, optimized design. These Cisco rugged switches bring simplicity, flexibility, and security to the network edge, and are optimized for size, power, and performance.

From their end-to-end security architecture to delivering centralized automation and scale with Cisco intent-based networking, the Cisco Catalyst IE3x00 family is the perfect solution to your switching needs in almost any use case.

Cisco Embedded Services 3300 Series Switches (ESS3300) revolutionize Cisco's embedded networking portfolio with 1G/10G capabilities. ESS3300 switches are optimized to meet specialized form-factor, ruggedization, port density, and power needs of many applications requiring customization. They complement Cisco's off-the-shelf Industrial Ethernet switching portfolio.

On ESS3300, the small form factor, board configuration options, and optimized power consumption provide Cisco partners and integrators the flexibility to design custom solutions for defense, oil and gas, transportation, mining, and other verticals. The ESS3300 runs the trusted and feature-rich Cisco IOS XE Software, allowing Cisco partners and integrators to offer their customers the familiar Cisco IOS CLI and management experience on their ESS3300 solutions.

New Features for Cisco Catalyst IE and ESS Switches in Cisco IOS XE 17.12.x

There are no new features in Cisco IOS XE 17.12.8. It is a maintenance release.

There are no new features in Cisco IOS XE 17.12.7a. It is a maintenance release.

There are no new features in Cisco IOS XE 17.12.5. It is a maintenance release.

There are no new features in Cisco IOS XE 17.12.4. It is a maintenance release.

There are no new features in Cisco IOS XE 17.12.3. It is a maintenance release.

There are no new features in Cisco IOS XE 17.12.2. It is a maintenance release.

The following features in 17.12.1 apply to IE3x00, IE3100, and ESS3300 switches unless mentioned otherwise.

Feature Name	License Level	Description	Supported Platforms	Related Document
MACsec CLI to change between "Must Secure" and "Should Secure"	Network Essentials	This feature gives you the option to allow unencrypted traffic to flow until an MKA session is secured. After the MKA session is secured, only encrypted traffic can flow.	IE3200, IE3300, IE3400, IE3400H	MACsec and the MACsec Key Agreement (MKA) Protocol
IE3100 NTP to PTP translation	Network Essentials	The IE3100 supports NTP to PTP translation, which allows you to use Network Time Protocol (NTP) as a time source for Precision Time Protocol (PTP).	IE3100	Configuring Precision Time Protocol

Important Notes

SSH Algorithms for Common Criteria Certification Limitation

Starting from Cisco IOS XE Release 17.10, the following Key Exchange and MAC algorithms are removed from the default list:

- Key Exchange algorithm:
  - diffie-hellman-group14-sha1
- MAC algorithms:
  - hmac-sha1
  - hmac-sha2-256
  - hmac-sha2-512




Note You can use the **ip ssh server algorithm kex** command to configure the Key Exchange algorithm and the **ip ssh server algorithm mac** command to configure the MAC algorithms.

IOx Support for IE3300 Switches

To see if the IE-3300-8P2S switch or IE-3300-8T2S switch supports IOx application environment, check the Hardware Version ID on the switch label. The Hardware Version ID is in the upper-right corner of the label, as shown in the following illustration. Support for the feature is available only with Hardware Version ID 06 or later. In the following illustration, the Version ID appears as "V06" at the end of the string inside the red rectangle in the upper-right corner of the label.

Figure 1: IE3300 Switch Label



You also can see the Version ID by entering the **show version** command and examining the output, as shown in the following example:

```
IE-3300#show version
Base Ethernet MAC Address          : b0:c5:3c:99:c8:a0
Motherboard Assembly Number        : 73-101289-11
Motherboard Serial Number          : FOC27151WEZ
Model Revision Number              : V06
Motherboard Revision Number        : B
Model Number                       : IE-3300-8T2S
System Serial Number               : FCW2507P4CV
Top Assembly Part Number           : 68-102662-01
Top Assembly Revision Number       : B0
System FPGA version                : 0.89.2
CIP Serial Number                  : 0x1999C8A0
SKU Brand Name                     : Cisco
```

IE-3300-8U2X and IE-3300-8T2X switches have supported IOx since the Cisco IOS-XE 17.4.1 release.

Startup Config is Always Read from Flash

Beginning in Cisco IOS XE Release 17.10.1, the startup configuration is always read from flash. The latest configuration is available only in flash when you save the running config, irrespective of the booted media (for example, flash, sdflash, or usbflash) and the boot mode (install or bundle).

Note Also beginning in the Cisco IOS XE Release 17.10.1, you can configure Cisco Catalyst embedded switches to use USB Flash as the primary boot device. See the Cisco IOS XE Migration Guide for IIoT Switches on cisco.com.

SMU Installation: Boot in Install Mode

Software Maintenance Upgrade (SMU) installation is no longer supported in bundle mode. Previously, SMU installation was supported in both bundle boot and install mode. Beginning in Cisco IOS XE 17.9.1, SMU supports patching using install mode only.

SMU installation stops if the device is booted up in bundle mode and syslog messages are displayed. You must boot the switch in install mode to support SMU installation.

If the device is booted up in install mode, SMU installation continues to work as before.

IE3100: Booting Install Image from SD Card

Booting an install image (packages.conf) from SD card is not recommended. After factory reset, to perform a swap drive sync from SD card to internal flash memory, you must manually boot the image available in the emergency partition so that the swap drive auto restore will occur from the emergency image.

For more information about the SD swap drive, see Configuring SD Swap Drive.

IE3400: Hardware Changes may Require Action

Some hardware components on the Cisco Catalyst IE3400 Rugged Series and Cisco Catalyst IE3400 Heavy Duty Series switches have changed. The changes, which are automatically handled by the IOS XE software, do not affect switch functionality or the ordering process. New units shipped after May 31, 2022 have the hardware change.

However, you may need to upgrade the software, depending on which base switch and expansion module you have, as shown in the following table.



Note For detailed information about affected hardware versions, supported software releases, and instructions for different scenarios, see Field Notice Title on Cisco.com.

If you have...	Then...
Older versions (shipped before May 31, 2022) of the base switch and expansion module	No action is required.
Newer versions (shipped after May 31, 2022) of the base switch and expansion module	Deploy one of the supported releases of IOS-XE. Refer to Field Notice Title on Cisco.com for details that are appropriate to your deployment.
Newer version of the base switch with an older version of the expansion module	
Older version of the base switch with a newer version of the expansion module	

FPGA Profile

FPGA Profile is supported in Cisco IOS XE release 17.8 and later. In a Cisco IOS XE upgrade from an earlier release that does not support FPGA Profile, for example, an upgrade from Cisco IOS XE 17.7.1 to 17.8.1, the default FPGA Profile is installed. Any features controlled by FPGA Profile that are configured in the switch running the earlier release and that are not included in the default profile will be rejected.



Note This feature is supported for Cisco Catalyst IE3400 Rugged Series Switches and Cisco Catalyst IE3400 Heavy-Duty Series Switches.

For example, CTS IPv6 is not supported in the default profile, so CTS IPv6 configurations are rejected during bootup after the upgrade. Similarly, after a Cisco IOS XE upgrade where the cts-ipv6 profile is loaded, existing PRP configurations are rejected upon bootup.

To keep the existing profile and feature configurations after an upgrade:

1. After booting the switch, select the required FPGA Profile as described in "Changing the FPGA Profile", in System Management Configuration Guide, Cisco Catalyst IE3x00 Rugged, IE3400 Heavy Duty, and ESS3300 Series Switches, chapter "Configuring FPGA Profile".

   Do not copy running-config to startup-config or write memory.

2. Reload the switch.

   The required feature configurations will not be discarded because they are supported by the selected profile.

PoE Limitation on IE3x00

Even when using power supplies that can provide up to a supported maximum (for example, 170, 240, or 480 W) for the PoE budget, the PoE budget for the IE3x00 defaults to 125 W regardless of the power supplies used. You can configure the power budget to use the maximum.



Note Before changing the power budget, the minimum power requirements for the switch need to be considered as well. Please refer to the data sheet for your switch for more details.

The attached power supply powers the IE3x00 switch operation as well as PoE power. When increasing the maximum PoE budget, you must subtract the power draw of the IE3x00 switch from the capacity of the attached power supply. You do so to prevent the IE3x00 switch from overdrawing the capacity of the attached power supply. For example, the IE3400 switch with an expansion module supports a maximum PoE budget of 480W. The IE3400-8P2S with an attached IEM-3400-8P draws 67W. With a 480W capacity power supply, the maximum you should configure the PoE budget is (480W-67W) 413W.

To use the power supply's maximum supported wattage for the PoE budget, configure the power supply max wattage in global configuration mode as follows:

1. Verify the maximum amount that the power supplies support for the PoE budget.
2. Subtract the operating power of the IE3x00 switch according to its datasheet from the maximum capacity of the power supply. This is your maximum PoE budget.
3. Enter **power inline max** *max-wattage* to increase the PoE budget based on the power supplies used.

   max-wattage is the maximum available PoE power.

IE3200 and IE3300 with 10Mbps or 100Mbps speed in Half-Duplex Mode

CRC errors were observed on the IE3200 and IE3300 platforms when the switch is configured with 10 or 100 Mbps speed in half-duplex mode.

As a workaround, configure **no ptp enable** on the half-duplex interface. This improves ingress and egress latencies considerably and ensures that there are no late collisions (and therefore, no CRC errors).

The issue and workaround apply to Cisco IOS XE releases 17.3.5 and later.

L3 ACL limitation on usage of L4OP in ACLs

Layer 4 Operator (L4OP) in ACLs is limited by the hardware to a maximum of 8 L4OP (range and gt) for UDP and 8 L4OP for TCP, for a total of 16 global L4OP. Keep in mind that the **range** operator consumes 2 L4OP.

The L4OPs include: gt (greater than), lt (less than), neq (not equal), eq (equal), range (inclusive range).

Cisco Catalyst IE and ESS Switches: Model Numbers (17.12.x)

The following table lists the supported hardware models and the default license levels they are delivered with. For information about the available license levels, see section *License Levels*.

Model Number	Default License Level	Description
IE-3100-4T2S-E	Network Essentials	4x1-Gigabit Ethernet 10/100/1000 RJ45 ports, 2x 100/1000 SFP fiber ports
IE-3100-8T2C-E	Network Essentials	8x1-Gigabit Ethernet 10/100/1000 RJ45 ports, 2x dual-purpose 1000Base-T RJ45 or 2 100/1000 SFP fiber ports
IE-3100-8T4S-E	Network Essentials	8x1-Gigabit Ethernet 10/100/1000 RJ45 ports, 4x 100/1000 SFP fiber ports
IE-3100-18T2C-E	Network Essentials	18x1-Gigabit Ethernet 10/100/1000 RJ45 ports, 2x dual-purpose 1000Base-T RJ45 or 2x 00/1000 SFP fiber ports
IE-3105-8T2C-E	Network Essentials	8x Gigabit Ethernet 10/100/1000 RJ45 ports, 2x dual-purpose 1000Base-T RJ45 or 2x 100/1000 SFP fiber ports
IE-3105-18T2C-E	Network Essentials	18x Gigabit Ethernet 10/100/1000 RJ45 ports, 2x dual-purpose 1000Base-T RJ45 or 2x 100/1000 SFP fiber ports
ESS-3300-NCP-E	Network Essentials	Main Board without a cooling plate 2 ports of 10 GE fiber, 8 ports of GE copper. 4 of the 8 GE copper ports can also be combo ports. Terminal Power: 16W
ESS-3300-NCP-A	Network Advantage	Main Board without a cooling plate 2 ports of 10 GE fiber, 8 ports of GE copper. 4 of the 8 GE copper ports can also be combo ports. Terminal Power: 16W

Model Number	Default License Level	Description
ESS-3300-CON-E	Network Essentials	Main Board conduction cooled 2 ports of 10 GE fiber, 8 ports of GE copper. 4 of the 8 GE copper ports can also be combo ports Terminal Power: 16W
ESS-3300-CON-A	Network Advantage	Main Board conduction cooled 2 ports of 10 GE fiber, 8 ports of GE copper. 4 of the 8 GE copper ports can also be combo ports Terminal Power: 16W
ESS-3300-24T-NCP-E	Network Essentials	Main Board with a 16p Expansion Board without a cooling plate 2 ports of 10 GE fiber, 24 ports of GE copper 4 of 8 GE ports can be combo ports on mainboard 4 of 16 GE ports can be combo ports on expansion board Terminal Power: 24W
ESS-3300-24T-NCP-A	Network Advantage	Main Board with a 16p Expansion Board without a cooling plate 2 ports of 10 GE fiber, 24 ports of GE copper 4 of 8 GE ports can be combo ports on mainboard 4 of 16 GE ports can be combo ports on expansion board Terminal Power: 24W
ESS-3300-24T-CON-E	Network Essentials	Main Board with a 16p Expansion Board conduction cooled 2 ports of 10 GE fiber, 24 ports of GE copper 4 of 8 GE ports can be combo ports on mainboard 4 of 16 GE ports can be combo ports on expansion board Terminal Power: 24W

Model Number	Default License Level	Description
ESS-3300-24T-CON-A	Network Advantage	Main Board with a 16p Expansion Board conduction cooled 2 ports of 10 GE fiber, 24 ports of GE copper 4 of 8 GE ports can be combo ports on mainboard 4 of 16 GE ports can be combo ports on expansion board Terminal Power: 24W
IE-3200-8T2S-E	Network Essentials	8x1-Gigabit Ethernet 10/100/1000 RJ45 ports, 2 fiber 100/1000 SFP-based ports, non-PoE
IE-3200-8P2S-E	Network Essentials	8x1-Gigabit Ethernet 10/100/1000 PoE/PoE+ ports, 2 fiber 100/1000 SFP-based ports; PoE power budget of 240W
IE-3300-8T2S-E	Network Essentials	8x1-Gigabit Ethernet 10/100/1000 RJ45 ports, 2 fiber 100/1000 SFP-based ports, non-PoE
IE-3300-8P2S-E	Network Essentials	8x1-Gigabit Ethernet 10/100/1000 PoE/PoE+ ports, 2 fiber 100/1000 SFP-based ports; PoE power budget of 360W (including expansion module)
IE-3300-8T2S-A	Network Advantage	8x1-Gigabit Ethernet 10/100/1000 RJ45 ports, 2 fiber 100/1000 SFP-based ports, non-PoE
IE-3300-8P2S-A	Network Advantage	8x1-Gigabit Ethernet 10/100/1000 PoE/PoE+ ports, 2 fiber 100/1000 SFP-based ports; PoE power budget of 360W (including expansion module)
IE-3300-8T2X-A	Network Advantage	8x1 Gigabit Ethernet 10/100/1000 RJ45 ports, 2 fiber 1/10 Gigabit Ethernet SFP-based ports, non-PoE
IE-3300-8T2X-E	Network Essentials	8x1-Gigabit Ethernet 10/100/1000 RJ45 ports, 2 fiber 1/10 Gigabit Ethernet SFP-based ports, non-PoE
IE-3300-8U2X-E	Network Essentials	8x1-Gigabit Ethernet 10/100/1000 4PPoE (802.3bt type 3) ports, 2 fiber 1/10 Gigabit Ethernet SFP-based ports; PoE power budget of 480W
IE-3300-8U2X-A	Network Advantage	8x1-Gigabit Ethernet 10/100/1000 4PPoE (802.3bt type 3) ports, 2 fiber 1/10 Gigabit Ethernet SFP-based ports; PoE power budget of 480W
IE-3400-8T2S-E	Network Essentials	8x1-Gigabit Ethernet 10/100/1000 RJ45 ports, 2 fiber 100/1000 SFP-based ports, non-PoE

Model Number	Default License Level	Description
IE-3400-8T2S-A	Network Advantage	8x1-Gigabit Ethernet 10/100/1000 RJ45 ports, 2 fiber 100/1000 SFP-based ports, non-PoE
IE-3400-8P2S-E	Network Essentials	8x1-Gigabit Ethernet 10/100/1000 RJ45 ports, 2 fiber 100/1000 SFP-based ports with PoE
IE-3400-8P2S-A	Network Advantage	8x1-Gigabit Ethernet 10/100/1000 RJ45 ports, 2 fiber 100/1000 SFP-based ports with PoE
IE-3400H-8T-E	Network Essentials	8x1-Gbps X-Coded ports, 1 Alarm input and 1 Alarm output, 1 Console port, mini-change input for Single power source
IE-3400H-8T-A	Network Advantage	8x1-Gbps X-Coded ports, 1 Alarm input and 1 Alarm output, 1 Console port, mini-change input for Single power source
IE-3400H-8FT-E	Network Essentials	8x-100-Mbps D-coded ports, 1 Alarm input and 1 Alarm output, 1 Console port, Mini-change input for Single Power Source .
IE-3400H-8FT-A	Network Advantage	8x-100-Mbps D-coded ports, 1 Alarm input and 1 Alarm output, 1 Console port, Mini-change input for Single Power Source .
IE-3400H-16T-E	Network Essentials	16x1-Gbps X-Coded ports, 1 Alarm input and 1 Alarm output, 1 Console port, mini-change input for Single power source
IE-3400H-16T-A	Network Advantage	16x1-Gbps X-Coded ports, 1 Alarm input and 1 Alarm output, 1 Console port, mini-change input for Single power source
IE-3400H-16FT-E	Network Essentials	16x-100-Mbps D-coded ports, 1 Alarm input and 1 Alarm output, 1 Console port, Mini-change input for Single Power Source .
IE-3400H-16FT-A	Network Advantage	16x-100-Mbps D-coded ports, 1 Alarm input and 1 Alarm output, 1 Console port, Mini-change input for Single Power Source .
IE-3400H-24T-E	Network Essentials	24x1-Gbps X-Coded ports, 1 Alarm input and 1 Alarm output, 1 Console port, mini-change input for Single power source
IE-3400H-24T-A	Network Advantage	24x1-Gbps X-Coded ports, 1 Alarm input and 1 Alarm output, 1 Console port, mini-change input for Single power source
IE-3400H-24FT-E	Network Essentials	24x-100-Mbps D-coded ports, 1 Alarm input and 1 Alarm output, 1 Console port, Mini-change input for Single Power Source .

Model Number	Default License Level	Description
IE-3400H-24FT-A	Network Advantage	24x-100-Mbps D-coded ports, 1 Alarm input and 1 Alarm output, 1 Console port, Mini-change input for Single Power Source .

WebUI System Requirements

The WebUI is a web browser-based switch management tool that runs on the switch. The following subsections list the hardware and software required to access the WebUI.

Minimum Hardware Requirements

Processor Speed	DRAM	Number of Colors	Resolution
233 MHz minimum[1]	512 MB[2]	256	1280 x 800 or higher

[1] We recommend 1 GHz
[2] We recommend 1 GB DRAM

Software Requirements

Operating Systems

- Windows 10 or later
- Mac OS X 10.9.5 or later

Browsers

- Google Chrome: Version 59 or later (On Windows and Mac)
- Microsoft Edge
- Mozilla Firefox: Version 54 or later (On Windows and Mac)
- Safari: Version 10 or later (On Mac)

Upgrading the Switch Software

This section covers the various aspects of upgrading or downgrading the device software.

Note See the Cisco IOS XE Migration Guide for IIoT Switches for the latest information about upgrading and downgrading switch software.

SSH Algorithms for Common Criteria Certification Limitation

Starting with Cisco IOS XE Release 17.10, the following Key Exchange and MAC algorithms are removed from the default list:

- Key Exchange algorithm:
  - diffie-hellman-group14-sha1
- MAC algorithms:
  - hmac-sha1
  - hmac-sha2-256
  - hmac-sha2-512



Note You can use the **ip ssh server algorithm kex** command to configure the Key Exchange algorithm and the **ip ssh server algorithm mac** command to configure the MAC algorithms.

Finding the Software Version

The package files for Cisco IOS XE software can be found on the system board's internal flash memory device (flash:) or an external USB, depending on the device configuration.

You can use the **show version** privileged EXEC command to see the software version that is running on your switch.



Note Although the **show version** output always shows the software image running on the switch, the model name shown at the end of this display is the factory configuration and does not change if you upgrade the software license.

You can also use the **dir** *filesystem:* privileged EXEC command to see the names and versions of other software images that you might have stored in flash memory.

Software Images 17.12.x

The following table provides the file names for the IOS XE 17.12.x software image for Cisco Catalyst IE3x00 Rugged, IE3400 Heavy Duty, and ESS3300 Series Switches and Cisco Catalyst IE3100 Rugged Series Switches.

Release	Image Type	File Name
Cisco IOS XE 17.12.8	Universal	ie3x00-universalk9.17.12.08.SPA.bin
		ess3x00-universalk9.17.12.08.SPA.bin
		ie31xx-universalk9.17.12.08.SPA.bin

Release	Image Type	File Name
Cisco IOS XE 17.12.7a	Universal	ie3x00-universalk9.17.12.07a.SPA.bin
		ess3x00-universalk9.17.12.07a.SPA.bin
		ie31xx-universalk9.17.12.07a.SPA.bin
Cisco IOS XE 17.12.6	Universal	ie3x00-universalk9.17.12.06.SPA.bin
		ess3x00-universalk9.17.12.06.SPA.bin
		ie31xx-universalk9.17.12.06.SPA.bin
Cisco IOS XE 17.12.5	Universal	ie3x00-universalk9.17.12.05.SPA.bin
		ess3x00-universalk9.17.12.05.SPA.bin
		ie31xx-universalk9.17.12.05.SPA.bin
Cisco IOS XE 17.12.4	Universal	ie3x00-universalk9.17.12.04.SPA.bin
		ess3x00-universalk9.17.12.04.SPA.bin
		ie31xx-universalk9.17.12.04.SPA.bin
Cisco IOS XE 17.12.3	Universal	ie3x00-universalk9.17.12.03.SPA.bin
		ess3x00-universalk9.17.12.03.SPA.bin
		ie31xx-universalk9.17.12.03.SPA.bin
Cisco IOS XE 17.12.2	Universal	ie3x00-universalk9.17.12.02.SPA.bin
		ess3x00-universalk9.17.12.02.SPA.bin
		ie31xx-universalk9.17.12.02.SPA.bin
Cisco IOS XE 17.12.1	Universal	ie3x00-universalk9.17.12.01.SPA.bin
		ess3x00-universalk9.17.12.01.SPA.bin
		ie31xx-universalk9.17.12.01.SPA.bin

Automatic Boot Loader Upgrade

When you upgrade from the existing release on your switch to a later release for the first time, the boot loader may be automatically upgraded, based on the hardware version of the switch. If the boot loader is automatically upgraded, it will take effect on the next reload.

For subsequent Cisco IOS XE releases, if there is a new bootloader in that release, it may be automatically upgraded based on the hardware version of the switch when you boot up your switch with the new image for the first time.

Caution Do not power cycle your switch during the upgrade.

Scenario	Automatic Boot Loader Response

When you boot Cisco IOS XE for the first time	Boot loader may be upgraded to version "8.1.2" for IE3x00 and ESS-3300.
	`Checking Bootloader upgrade...`
	`…`
	`Bootloader upgrade successful`

Software Installation Commands

Note For the **install** command to be successful, ensure that available flash space is at least twice the image size. If there is not enough space available in flash, you are advised to free up space in flash either by issuing the **install remove inactive** command or to manually clean up the flash by removing unwanted core files or any other files that occupy a large amount of space in flash.

Summary of Software Installation Commands for Install Mode	
To install and activate the specified file, and to commit changes to be persistent across reloads: **`install add file`** *`filename`* [**`activate commit`**]	
add file tftp: *filename*	Copies the install file package from a remote location to the device and performs a compatibility check for the platform and image versions.
activate [**auto-abort-timer**]	Activates the file, and reloads the device. The **auto-abort-timer** keyword automatically rolls back image activation.
commit	Makes changes persistent over reloads.
remove	Deletes all unused and inactive software installation files.

Licensing

For information about the licensing packages for features available on Cisco Catalyst IE3x00 Rugged, IE3400 Heavy Duty, and ESS3300 Series Switches and Cisco Catalyst IE3100 Rugged Series Switches, see Licensing on the Cisco Catalyst IE3x00 and IE3100 Rugged, IE3400 Heavy Duty, and ESS3300 Series Switches.

Caveats

Caveats describe unexpected behavior in Cisco IOS XE releases. Caveats listed as open in a prior release are carried forward to the next release as either open or resolved.

Cisco Bug Search Tool

Cisco Bug Search Tool is a web-based tool that acts as a gateway to the Cisco bug tracking system that maintains a comprehensive list of defects and vulnerabilities in Cisco products and software. BST provides you with detailed defect information about your products and software.

Click the link for the caveat in the sections below to view details for the caveat in Bug Search Tool.

Open Caveats in Cisco IOS XE Dublin 17.12.x

Identifier	Description
CSCwi95368	IE3300 switches TFTP timed out when blocksize is set to 8192
CSCwt38298	IE3200 Memory Leak in Pool Manager and Possible Crashes
CSCwt95175	IE 3x00 ends up in Device Unresponsive ({"i18n":{"code":"NCIM12011"}) state when added to CATC inventory

Resolved Caveats in Cisco IOS XE Dublin 17.12.8

No customer-impacting bugs were fixed in this release.

Resolved Caveats in Cisco IOS XE Dublin 17.12.7a

Identifier	Description
CSCwq73986	Connectivity issue between ccv-sensor-app and default gateway
CSCwr62046	ICMPv6 packets are duplicated when device tracking is enabled on the interface
CSCwr63196	IE3100 is duplicating the IPv6 packets received
CSCwr81607	IE3400 SNMP Multicast Counters not working - ifOutMulticastPkts
CSCws17503	Broadcast traffic is leaking over a routed port
CSCws35687	L4 ACLs not summarised properly causing some entries to not take effect
CSCwq80434	With \"reload\" command, switchports stay up for an extended time after the switch stops forwarding traffic.
CSCwr05475	IE3400 - 17.12.3 - Memory Leak observed in SNMP ENGINE
CSCwr42830	IE3300 - MKA session fails to come up after upgrade or power cycle
CSCwn56770	IE3100 | SNMP IfOperstatus shows as \"Not Present\" regardless of the actual status.

Resolved Caveats in Cisco IOS XE Dublin 17.12.6

Identifier	Description
CSCwm51530	IE3x00: Observed Crash in \"imsp_led_init: fail to get max physical port for slot =1\
CSCwo15432	PTP stop working after ACL with permit ip any any
CSCwo96008	PTP not processed/forwarded on ESS3300 running 17.12.04
CSCwp24973	Code and GSDML changes for SFP 10G-SR-S
CSCwh07580	[EAPTLS based] MACsec session not coming up intemitently
CSCwi02000	cmcc crash observed due to Sensor has exceeded it's maximum number of read errors
CSCwj82708	Intermittent network connectivity with interfaces with speed/duplex of 100/half.
CSCwm39413	ESS3300: port power deny power if lower consumption value configured, recovers with port reset
CSCwn88892	%IMSP_ACLMGR-3-INVALIDACL: Add access-list failed error on IE3400 switches
CSCwn98466	IE3100-Major Alarm Relay Fault due to Over temperature Spike
CSCwo33351	IE3xxx: Observed \"rep bpduleak\" CLI in Latest image
CSCwp05951	IE3400 increments input/CRC/L2nat discards/Ethernet-controller stats unexpectedly with L2nat config.
CSCwp38345	DHCP snooping dropping DHCP discover message for non CDP devices
CSCwp38501	IE-3300-8T2S-E switch not forwarding STCN packet intermittently
CSCwp84508	Device with IPv6 ACL on 13+ Interfaces crashes on reload

Resolved Caveats in Cisco IOS XE Dublin 17.12.5

Identifier	Description
CSCwj97078	IE3400: Traffic is not forwarded over mrouter ports.
CSCwk86434	IE3100 - configuration failed to parse with a good ciscortr.cfg.
CSCwm79627	Setting collision domain limit on port-channel causes device to crash with Segmentation fault(11).
CSCwm85265	REP ZTP functioning incoherent.
CSCwn47744	Device not able to ping on trunk port when \"vlan dot1q tag native\" is configured globally.

Identifier	Description
CSCwk30765	IE3400 PNP/Autoinstall failing.
CSCwm33057	Slowness on ie-3100 when polling snmp OIDs.
CSCwm36038	ESS-3300 forwards unicast traffic to all promiscuous ports.
CSCwm47470	Endpoints with 10Mbps speed in Half-Duplex Mode drops the connection.
CSCwm48006	C9300 fails to establish proper STP connection with connected device when interface goes down.
CSCwn62607	IE3100-PN connect issues due to out of AR resources.
CSCwm50612	IE3100: SNMP ifOperStatus MIB incorrectly reporting port-channel interface down.
CSCwj68054	MAT event not working on EEM for IE3400 switches.

Resolved Caveats in Cisco IOS XE Dublin 17.12.4

Identifier	Description
CSCwj23080	IE-3400 crashes after clear cts due segmentation fault.
CSCwk70287	Temperature error syslogs observed in IE3K platforms
CSCwi64278	ESS-3300 | Multicast Packets are dropped with Source Guard Feature Enabled.
CSCwi66479	Intermittent packet drops and log \"Error: LPM IPv6 100% capacity is reached.
CSCwi69364	NETCONF get config returns < add-vlans > < add > and < remove > after changing allowed trunk VLANs via CLI
CSCwi90435	ESS3300- Stopping unknown unicast needs a toggle to work after reload.
CSCwj70605	IE3300 drops ARP packets for a VLAN, when DAI is configured globally on any VLAN
CSCwj91206	Profinet and LLDP configuration is not visible in startup config and is missing after reload
CSCwk29015	Normal vlan device not pinging when dhcpsnooping,arp inspection & IPDT enabled on pvlan interface

Resolved Caveats in Cisco IOS XE Dublin 17.12.3

Identifier	Description
CSCwh79813	Etherchannel Mismatch Triggers Loop (mac-flap).
CSCwi49051	IE-3300 Configuration Issue for IP Source Guard.

Identifier	Description
CSCwi80954	IE-3300 drops unicast DHCP Discover packet if DHCP Snooping is enabled globally on L3 interfaces.
CSCwi01476	Memory leak in "Pool manager", small buffers are leaking memory due to PTP packets.
CSCwi23741	EAP-TLS auth issue after updating IE3400 Switches from 17.1.x or 17.3.x releases to 17.7.x and above.

Resolved Caveats in Cisco IOS XE Dublin 17.12.2

Identifier	Description
CSCwh87343	Cisco IOS XE Software Web UI Privilege Escalation Vulnerability
CSCwh38767	IE3x00: Interface input errors(ifInErrors) is getting reset on every read
CSCwh75542	IE3x00 - Switch increasing memory usage over a period of time, for a frequent snmp query
CSCwf80202	REP Alt port does not return to the designated port after recovering from the malfunction
CSCwf83475	IE3x00: Moving port across vlan, MRP ring does not converge
CSCwe82679	IE3x00 - AAA doesn't work with RADIUS non-standard port
CSCwf74861	REP is not working correctly on Rugged IE-3x00 with MACSEC enabled on REP ports

Resolved Caveats in Cisco IOS XE Dublin 17.12.1

Identifier	Description
CSCwd74622	User in Isolated PVLAN is Unable to Ping Primary VLAN SVI
CSCwd97578	Log is generate after link flapping: Error: LPM IPv4 100% capacity is reached
CSCwe36005	[SNMP] Traceback observed with get-bulk of LRE MIB's
CSCwe18850	802.1x and MAB authentication fails against the RADIUS server over IPv6 transport
CSCwd73631	IE3300 could not handle fragmented PIM bootstrap received in Trunk port
CSCwe44846	Switch reaches critical memory level when running CV with 2GB of memory

Troubleshooting

For the most up-to-date, detailed troubleshooting information, see the Cisco TAC website at this URL:

https://www.cisco.com/en/US/support/index.html

Go to **Product Support** and select your product from the list or enter the name of your product. Look under Troubleshoot and Alerts to find information for the problem that you are experiencing.

Related Documentation

Information about Cisco IOS XE at this URL: https://www.cisco.com/c/en/us/products/ios-nx-os-software/ios-xe/index.html

All support documentation for Cisco Catalyst IE3100 Rugged Series Switches is at this URL: https://www.cisco.com/c/en/us/support/switches/catalyst-ie3100-rugged-series/series.html

All support documentation for Cisco Catalyst IE3100H Heavy Duty Series Switches is at this URL: https://www.cisco.com/c/en/us/support/switches/catalyst-ie3100-heavy-duty-series/series.html

All support documentation for Cisco Catalyst IE3200 Rugged Series Switches is at this URL: https://www.cisco.com/c/en/us/support/switches/catalyst-ie3200-rugged-series/tsd-products-support-series-home.html

All support documentation for Cisco Catalyst IE3300 Rugged Series Switches is at this URL: https://www.cisco.com/c/en/us/support/switches/catalyst-ie3300-rugged-series/tsd-products-support-series-home.html

All support documentation for Cisco Catalyst IE3400 Rugged Series Switches is at this URL: https://www.cisco.com/c/en/us/support/switches/catalyst-ie3400-rugged-series/tsd-products-support-series-home.html

All support documentation for Cisco Catalyst IE3400H Heavy Duty Series Switches is at this URL: https://www.cisco.com/c/en/us/support/switches/catalyst-ie3400-heavy-duty-series/tsd-products-support-series-home.html

All support documentation for Cisco ESS3300 Series Switches is at this URL: https://www.cisco.com/c/en/us/support/switches/embedded-service-3000-series-switches/tsd-products-support-series-home.html

Cisco Validated Designs documents at this URL: https://www.cisco.com/go/designzone

To locate and download MIBs for selected platforms, Cisco IOS releases, and feature sets, use Cisco MIB Locator found at the following URL: http://www.cisco.com/go/mibs

Communications, Services, and Additional Information

- To receive timely, relevant information from Cisco, sign up at Cisco Profile Manager.
- To get the business impact you're looking for with the technologies that matter, visit Cisco Customer Experience.
- To submit a service request, visit Cisco Support.

- To discover and browse secure, validated enterprise-class applications, products, solutions, and services, visit Cisco Networking App Marketplace.
- To obtain general networking, training, and certification titles, visit Cisco Press.
- To find warranty information for a specific product or product family, access Cisco Warranty Finder.

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: https://www.cisco.com/c/en/us/about/legal/trademarks.html. Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1721R)

Any Internet Protocol (IP) addresses and phone numbers used in this document are not intended to be actual addresses and phone numbers. Any examples, command display output, network topology diagrams, and other figures included in the document are shown for illustrative purposes only. Any use of actual IP addresses or phone numbers in illustrative content is unintentional and coincidental.

© 2023–2026 Cisco Systems, Inc. All rights reserved.