

Configuration Deployment

This chapter describes how to download configuration changes to one or more managed devices.

- Configuration deployment, on page 1
- Requirements and prerequisites for deployment management, on page 12
- Best practices for deploying configuration changes, on page 12
- Configuration deployment, on page 13
- Deployment management, on page 24

Configuration deployment

Configuration deployment is a management process that enables centralized control and distribution of device settings from Cloud-Delivered Firewall Management Center to managed devices.

Configuration changes that require deployment

Cloud-Delivered Firewall Management Center marks out-of-date policies with red status text that indicates how many of its targeted devices need a policy update. Redeploy the policy to the devices to clear this status.

Deployment required

You must deploy changes after these configuration updates:

- Modifying an access control policy: any changes to access control rules, the default action, policy targets, Security Intelligence filtering, advanced options including preprocessing, and so on.
- Modifying any of the policies that the access control policy invokes: the SSL policy, network analysis policies, intrusion policies, file policies, identity policies, or DNS policies.
- Changing any reusable object or configuration used in an access control policy or policies it invokes:
  - network, port, VLAN tag, URL, and geolocation objects
  - Security Intelligence lists and feeds
  - application filters or detectors
  - intrusion policy variable sets
  - file lists

    - decryption-related objects and security zones

- Updating intrusion rules (SRU/LSP) or the vulnerability database (VDB).
- Upgrading managed devices.

You can change some of these configurations from multiple places in the web interface. For example, you can modify security zones using the object manager (**Objects**), but modifying an interface type in a device configuration (**Devices** > **Device Management**) can also change a zone and require a deployment.

Deployment not required

These updates do not require a deployment:

- Security Intelligence updates to feeds and the global Block or Do Not Block lists.
- URL filtering data updates.
- Geolocation database (GeoDB) updates.

Deployment preview

A deployment preview is a snapshot that provides all the policy and object changes to be deployed on the device.

The policy changes include the new policies, changes in the existing policies, and the deleted policies. The object changes include the added and modified objects which are used in policies. The unused object changes are not displayed because they are not deployed on the device.

- **Comparison View**: Displays a side-by-side comparison of all the device configuration changes made since your last deployment.
- **Advanced View**: Displays the pending CLI commands to be applied to the device.

For more information about viewing the deployment preview, refer to Deploy configuration changes, on page 14.

The preview shows all the default values, even when they are not altered, along with the other configured settings when an interface or a platform settings policy is added for the first time. Similarly, the high availability-related policies and default values for settings are shown, even when they are not altered, in the first preview after a high availability pair is configured or disrupted.

To view changes due to an auto rollback, refer to Edit deployment settings.

Unsupported features:

- Object additions and attribute changes are displayed in the preview only if the objects are associated with any device or interface. Object deletions are not displayed.
- Preview is not supported for the policies:
    - High availability
    - Network discovery
    - Network analysis

    - Device settings

- User information at the rule level is not available for intrusion policies.
- The preview does not show the reordering of rules across policies.

  For DNS policies, reordered rules appear in the preview list as rule additions and deletions. For example, moving a rule from position 1 to position 3 in the rule order is displayed as if the rule was deleted from position 1 and added as a new rule in position 3. Similarly, when a rule is deleted, the rules under it are listed as edited rules as they have changed their positions. The changes are displayed in the final order in which they appear in the policy.
- Preview is not supported in these HA scenarios:
  - If a device was in standalone mode and if a chain is made, then an auto-deployment is triggered. For that particular job, preview is not supported. On hover over the **Preview** (), a message is displayed that it is a HA bootstrap deployment, and no preview is supported.
  - **Configuration groups** - Consider a flow in which a device was initially standalone. Subsequently, three deployments took place. In the fourth deployment, the device was a HA bootstrap deployment. After these, the user deploys devices 5, 6, and 7. The deployment 7 is an HA break deployment, and the user deploys devices 8, 9, and 10.

    In this flow, the preview between 3 and 5 is not supported because 4 was a HA deployment. Similarly, the preview between 8 and 3 is also not supported. Preview is supported only from 3 to 1, 7,6, 5, 4, and 10, 9, and 8.
  - If a device is broken (HA is broken) then the new device is considered as a fresh device.

Guidelines for selective policy deployment

The Cloud-Delivered Firewall Management Center allows you to select a specific policy within the list of all the changes on the device that are due for deployment and deploy only the selected policy.

This table describes the policies that suppot selective deployment.

Table 1: Policies that support selective deployment

Type	Policy
Access control	• Access control policies • Prefilter policies • QoS policies
Threat prevention and inspection	• Intrusion policies • Malware and file policies • DNS policies

Type	Policy
Identity and discovery	• SSL / decryption policies • Identity policies • Network discovery
Device or network connectivity	• NAT policies • Routing policies • VPN policies

Use the this table to understand the constraints and conditions for applying selective policy deployment.

Table 2: Limitations for selective deployment

Type	Description	Scenarios
Full deployment	Full deployment is necessary for specific deploy scenarios, and the Firewall Management Center does not support selective deployment in such scenarios. If you encounter an error in such scenarios, you may choose to proceed by selecting all the changes for deployment on the device.	Full deployment is required for: • The first deployment after you upgrade devices. • The first deployment after you restore a device. • The first deployment after modifications to a device's interface settings. • The first deployment after modifications in the virtual router settings.
Associated policy deployment	The Cloud-Delivered Firewall Management Center identifies interdependent policies which are interlinked. When one of the interlinked policies is selected, the remaining interlinked policies are automatically selected.	Scenarios wherein an associated policy is automatically selected: • When a new object is associated with an existing policy. • When an existing policy's object is modified. Scenarios wherein multiple policies are automatically selected: • When a new object is associated with an existing policy, and the same object is already associated with other policies, all the associated policies are automatically selected. • When a shared object is modified, all the associated policies are automatically selected.

Type	Description	Scenarios
Interdependent policy changes (shown using color-coded tags)	The Cloud-Delivered Firewall Management Center dynamically detects dependencies in-between policies, and between the shared objects and the policies. The interdependency of the objects or policies is shown using color-coded tags.	Scenarios wherein color-coded interdependent policies or objects are automatically selected: • When all the out-of-date policies have interdependent changes. For example, when an access control policy, an intrusion policy, and a NAT policy are out-of-date. Since access control policy and NAT policy share an object, all policies are selected together for deployment. • When all out-of-date policies share an object, and the object is modified.
Access Policy Group specifications	Access Policy Group policies are listed together in the preview window under **Access Policy Group** when you click **View** ().	The scenarios and the expected behavior for Access Policy Group policies are: • If the access control policy is out-of-date, all other out-of-date policies under this group, except file policy and intrusion policy, are selected when the access control policy is selected for deployment. However, if the access control policy is out-of-date, intrusion and file policies can be individually selected or deselected irrespective of whether the access control policy is selected or not, unless there are any dependent changes. For example, if a new intrusion policy is assigned to an access control rule, it indicates that there are dependent changes, then both the access control policy and the intrusion policy will be automatically selected when either of them is selected. • If no access control policy is out-of-date, other out-of-date policies in this group can be selected and deployed individually.

System username

The Cloud-Delivered Firewall Management Center displays the username as **system** for specific management operations. This allows administrators to distinguish system-initiated actions from those performed by users.

The **system** username is applied to these operations:

- Rollback
- Upgrade
- Firewall Threat Defense backup and restore

- SRU update
- LSP update
- VDB update

Auto-enabling of application detectors

When you perform application control but disable required detectors, the Cloud-Delivered Firewall Management Center automatically enables the appropriate system-provided detectors upon policy deployment. If no system-provided detector exists for the application, the Cloud-Delivered Firewall Management Center enables the most recently modified user-defined detector.

Asset rediscovery with network discovery policy changes

When you deploy changes to a network discovery policy, the system deletes and then rediscovers MAC address, TTL, and hops information from the network map for the hosts in your monitored networks. Also, the affected managed devices discard any discovery data that has not yet been sent to the Cloud-Delivered Firewall Management Center.

Snort restart scenarios

A Snort restart scenario is a situation that

- causes the traffic inspection engine, referred to as the `Snort process`, on a managed device to restart,
- interrupts inspection until the process resumesWhether traffic drops during this interruption or passes without further inspection depends on how the assigned device handles traffic. Refer to Snort restart traffic behavior, on page 8., and
- may result in resource demands that cause a small number of packets to drop without inspection when you deploy.

Common snort restart triggers

Any of these scenarios cause the Snort process to restart:

- You deploy a specific configuration that requires the Snort process to restart. For more information, refer to Configurations that restart the snort process when deployed or activated, on page 10.
- You make a change that immediately restarts the Snort process. For more information, refer to Actions that immediately restart the snort process, on page 11.
- Traffic activates the currently deployed Automatic Application Bypass (AAB) configuration. For more information, refer Configure automatic application bypass.
- Enabling or disabling **Logging connection events to RAM disk** feature. For more information, refer the section **Log to Ramdisk** in Troubleshoot Drain of FMC Unprocessed Events.

Inspection interruption warnings during deployment

When you deploy configurations, the **Inspect Interruption** column in the deploy page indicates if a deployed configuration will restart the Snort process on the Firewall Threat Defense device. When the traffic inspection engine referred to as the `Snort process` restarts, inspection is interrupted until the process resumes. Whether traffic is interrupted or passes without inspection during the interruption depends on how the traffic is handled by the device. You can proceed with the deployment, cancel the deployment and modify the configuration, or delay the deployment until a time when deploying would have the least impact on your network.

During deployment, when the **Inspect Interruption** column indicates **Yes** and you expand the device configuration listing, an icon will highlight any configuration type that may restart the Snort process. Moving your pointer over the icon displays a message saying that deployment may interrupt traffic.

This table summarizes how the deploy page displays inspection interruption warnings.

Table 3: Inspection interruption indicators

Type	Inspect interruption	Description
Firewall Threat Defense	**Inspect Interruption** (Yes)	At least one configuration would interrupt inspection on the device if deployed, and might interrupt traffic depending on how the device handles traffic. You can expand the device configuration listing for more information.
	--	Deployed configurations will not interrupt traffic on the device.
	Undetermined	The system cannot determine if a deployed configuration may interrupt traffic on the device. Undetermined status is displayed before the first deployment after a software upgrade, or in some cases during a Support call.
	Errors ( )	The system cannot determine the status due to an internal error. Cancel the operation and click **Deploy** again to allow the system to redetermine the **Inspect Interruption** status. If the problem persists, contact Support.
sensor	--	The device identified as *sensor* is not the Firewall Threat Defense device; the system does not determine if a deployed configuration may interrupt traffic on this device.

For information on all configurations that restart the Snort process for all device types, see Configurations that restart the snort process when deployed or activated, on page 10.

Inspect traffic during policy apply


Inspect traffic during policy apply is an advanced access control policy general setting that enables managed devices to inspect traffic while configuration changes are applied, and allows inspection unless a deployed configuration requires the Snort process to restart.

Configuration options

You can configure this setting as follows:

- Enabled — Traffic is inspected during the deployment unless certain configurations require the Snort process to restart. When a Snort restart is not needed, the system first uses the currently deployed access control policy to inspect traffic, then switches to the policy being deployed.
- Disabled — Traffic is not inspected during the deployment. The Snort process always restarts when you deploy.

This graphic illustrates how Snort restarts can occur when you enable or disable **Inspect traffic during policy apply**.



Caution When you deploy, resource demands may result in a small number of packets dropping without inspection. Additionally, deploying some configurations restarts the Snort process, which interrupts traffic inspection. Whether traffic drops during this interruption or passes without further inspection depends on how the target device handles traffic. Refer to Snort restart traffic behavior, on page 8 and Configurations that restart the snort process when deployed or activated, on page 10.

Snort restart traffic behavior

This reference explains how different devices handle traffic when the Snort process restarts.

Table 4: The Firewall Threat Defense and the Firewall Threat Defense Virtual Restart Traffic Effects

Interface configuration	Restart traffic behavior
inline: **Snort Fail Open: Down**: disabled	dropped

Interface configuration	Restart traffic behavior
inline: **Snort Fail Open: Down**: enabled	passed without inspection Some packets can be delayed in buffer for several seconds before the system recognizes that Snort is down. This delay can vary depending upon the load distribution. However, the buffered packets are eventually passed.
routed, transparent (including EtherChannel, redundant, subinterface): **preserve-connection** enabled (**configure snort preserve-connection enable**; default) For more information, see *Cisco Secure Firewall Threat Defense Command Reference*.	existing TCP/UDP flows: passed without inspection so long as at least one packet arrives while Snort is down new TCP/UDP flows and all non-TCP/UDP flows: dropped Note that traffic drops even when **preserve-connection** is enabled for: • plaintext, passthrough prefilter tunnel traffic that matches an **Analyze** rule action or an **Analyze all tunnel traffic** default policy action • connections that do not match an access control rule and are instead handled by the default action • decrypted TLS/SSL traffic • a safe search flow • a captive portal flow
routed, transparent (including EtherChannel, redundant, subinterface): **preserve-connection** disabled (**configure snort preserve-connection disable**)	dropped
inline: tap mode	egress packet immediately, copy bypasses Snort
passive	uninterrupted, not inspected

Note In addition to traffic handling when the Snort process is down while it restarts, traffic can also pass without inspection or drop when the Snort process is busy, depending on the configuration of the Snort Fail Open **Busy** option (see Configure Inline Sets). A device supports either the Failsafe option or the Snort Fail Open option, but not both.

Note When the Snort process is busy but not down during configuration deployment, some packets may drop on routed, switched, or transparent interfaces if the total CPU load exceeds 60 percent.

Warning Do not reboot the system while the Snort Rule Update is in progress.

Snort-busy drops happen when snort is not able to process the packets fast enough. Lina does not know whether Snort is busy due to processing delay, or if is stuck or due to call blocking. When transmission queue is full, snort-busy drops occur. Based on Transmission queue utilization, Lina will try to access if the queue is being serviced smoothly.

Configurations that restart the snort process when deployed or activated

Deploying any of these configurations except AAB restarts the Snort process as described. Deploying AAB does not cause a restart, but excessive packet latency activates the currently deployed AAB configuration, causing a partial restart of the Snort process.

Access control policy advanced settings

- Deploy when **Inspect Traffic During Policy Apply** is disabled.
- Add or remove an SSL policy.

File policy

Deploy the first or last of any one of these configurations; note that while otherwise deploying these file policy configurations does not cause a restart, deploying non-file-policy configurations can cause restarts.

- Take either of these actions:
  - Enable or disable **Inspect Archives** when the deployed access control policy includes at least one file policy.
  - Add the first or remove the last file policy rule when **Inspect Archives** is enabled (note that at least one rule is required for **Inspect Archives** to be meaningful).
- Enable or disable **Store files** in a **Detect Files** or **Block Files** rule.
- Add the first or remove the last active file rule that combines the **Malware Cloud Lookup** or **Block Malware** rule action with an analysis option (**Spero Analysis or MSEXE**, **Dynamic Analysis**, or **Local Malware Analysis**) or a store files option (**Malware, Unknown**, **Clean**, or **Custom**).

Note that access control rules that deploy these file policy configurations to security zones or tunnel zones cause a restart only when your configuration meets these conditions:

- Source or destination security zones in your access control rule must match the security zones associated with interfaces on the target devices.
- Unless the destination zone in you access control rule is *any*, a source tunnel zone in the rule must match a tunnel zone assigned to a tunnel rule in the prefilter policy.

Identity policy

- When SSL decryption is disabled (that is, when the access control policy does not include an SSL policy), add the first or remove the last active authentication rule.

An active authentication rule has either an **Active Authentication** rule action, or a **Passive Authentication** rule action with **Use active authentication if passive or VPN identity cannot be established** selected.

Network discovery

- Enable or disable non-authoritative, traffic-based user detection over the HTTP, FTP, or MDNS protocols, using the network discovery policy.

Device management

- MTU: Change the highest MTU value among all non-management interfaces on a device.
- Automatic Application Bypass (AAB): The currently deployed AAB configuration activates when a malfunction of the Snort process or a device misconfiguration causes a single packet to use an excessive amount of processing time. The result is a partial restart of the Snort process to alleviate extremely high latency or prevent a complete traffic stall. This partial restart causes a few packets to pass without inspection, or drop, depending on how the device handles traffic.

TLS server identity discovery

Enabling or disabling **TLS Server Identity Discovery** will result in a Snort 2 restart.

Note Snort 3 does not restart when **TLS Server Identity Discovery** is enabled or disabled.

Updates

- System update: Deploy configurations the first time after a software update that includes a new version of the Snort binary or data acquisition library (DAQ).
- For managed devices running Snort 3, deploying configurations the first time after installing a vulnerability database (VDB) update may temporarily interrupt application detection, but there will be no traffic interruptions.

Actions that immediately restart the snort process

These actions immediately restart the Snort process without requiring deployment. How the restart affects traffic depends on how the target device handles traffic. Refer to Snort restart traffic behavior, on page 8.

Applications or application detectors

- Activate or deactivate a system or custom application detector.
- Delete an activated custom detector.
- **Save and Reactivate** an activated custom detector.
- Create a user-defined application.

When you perform any of these actions, a message warns you that continuing will restart the Snort process. The message allows you to cancel. The system restarts Snort on all managed devices in the current domain and any child domain.

High availability configuration

Create or break a Firewall Threat Defense high availability pair.

When you create or break a high availability pair, a message warns you that creating or breaking a high availability pair restarts the Snort process on the primary and secondary devices. The message allows you to cancel.

Requirements and prerequisites for deployment management

Before using the configuration deployment feature in the Cloud-Delivered Firewall Management Center, ensure you meet these requirements.

- You must have **Administrator**, **Network Admin**, or **Security Approver** privileges to access the deployment features.
- Before deploying policy changes, you can compare the differences between the current device configuration and the pending policy, ensuring accuracy before you finalize the deployment. To use this feature, you must have the appropriate access rights, valid licenses for the specific policy, and be in the correct domain context.
- You must enable REST API access to preview the changes before a deployment. To enable the REST API access, follow the steps in *Enabling REST API Access* in the *Cisco Secure Firewall Management Center Administration Guide*.

Best practices for deploying configuration changes

Reliable management connection

The management connection between the Cloud-Delivered Firewall Management Center and the device is a secure, TLS-1.3-encrypted communication channel between itself and the device.

To ensure reliable management connection, use a direct management path instead of routing management traffic through an additional encrypted tunnel, such as a Site-to-Site VPN. If the tunnel fails, you could lose management connectivity.

To maintain a reliable management connection, exclude management traffic from the VPN tunnel if it exits a VPN-terminating interface.

Caution Avoid routing a device's management connection through a VPN tunnel that terminates on the device itself. If a configuration update causes the tunnel to drop, you will lose the management connection and cannot recover the device configuration unless you connect directly to the device.

Maximum concurrent deployments

Avoid deploying to more than 25 percent of the maximum devices allowed for a Cloud-Delivered Firewall Management Center in the same deployment task. For example, for the FMCv300, the maximum deployment task size is 75 devices (25 percent of 300). Deploying concurrently to more devices can cause performance issues.

Deployment of shared policies

For best performance, deploy to devices that use the same policies. Create a separate deployment task for each group of devices that share policies.

Time to deploy and memory limitations

Deployment time depends on multiple factors, including:

- The configurations you send to the device. For example, if you dramatically increase the number of Security Intelligence entries you block, deployment can take longer.
- Device model and memory. On devices with less memory, deployment can take longer.

Keep your configurations within the capability of your devices. If you exceed the maximum number of rules or policies supported by a target device, Cloud-Delivered Firewall Management Center displays a warning. The maximum depends on a number of factors—not only memory and the number of processors on the device, but also on policy and rule complexity. For information on optimizing policies and rules, refer to Best practices for access control rules.

Use a maintenance window to lessen the impact of traffic interruptions

We *strongly* recommend you deploy in a maintenance window or at a time when interruptions will have the least impact.

- When you deploy, resource demands may result in a small number of packets dropping without inspection. Additionally, deploying some configurations restarts the Snort process, which interrupts traffic inspection. Whether traffic drops during this interruption or passes without further inspection depends on how the target device handles traffic. Refer to Snort restart traffic behavior, on page 8 and Configurations that restart the snort process when deployed or activated, on page 10.
- For the Firewall Threat Defense devices, the **Inspect Interruption** column in the **Deploy** dialog warns you when deploying might interrupt traffic flow or inspection. You can proceed with, cancel, or delay deployment. For more information, refer to Inspection interruption warnings during deployment, on page 7.

Configuration deployment

Configuration deployment is the process of deploying configuration and policy updates to your Fireall Threat Defense devices after you make changes. This process allows you to apply changes to multiple components including device configurations, security policies, and network discovery settings.

Deployment components

Deploying updates applies to these components:

- Device and interface configurations
- Device-related policies, such as NAT, VPN, QoS, and platform settings policy

- Access control and related policies: DNS, file, identity, intrusion, network analysis, prefilter, SSL
- Network discovery policy
- Intrusion rule updates
- Configurations and objects associated with any of these elements

You can configure the system for automatic deployment by scheduling a deploy task or by setting the system to deploy when importing intrusion rule updates. Automating policy deployment is especially useful if you allow intrusion rule updates to modify system-provided base policies for intrusion and network analysis. Intrusion rule updates can also modify default values for the advanced preprocessing and performance options in your access control policies.

You can view deployment status in the **Notifications** pane.

Deploy configuration changes

Apply new or updated device configurations to managed devices.

After you change a device configuration, you must deploy the changes for them to take effect. Deploy during a maintenance window or off-peak hours to minimize potential traffic and inspection disruption.

Caution When you deploy, resource demands may result in a small number of packets dropping without inspection. Additionally, deploying some configurations restarts the Snort process, which interrupts traffic inspection. Whether traffic drops during this interruption or passes without further inspection depends on how the target device handles traffic. Refer to Snort restart traffic behavior, on page 8 and Configurations that restart the snort process when deployed or activated, on page 10.

Before you begin

- Confirm that all managed devices use the same revision of the Security Zones object. If you have edited security zone objects: Do not deploy configuration changes to any device until you edit the zone setting for interfaces on *all* devices you want to sync. You must deploy to all managed devices at the same time.
- To preview the deployment changes, enable REST API access. To enable the REST API access, follow the steps in *Enabling REST API Access* in the *Cisco Secure Firewall Management Center Administration Guide* .

Note The deployment process fails if the device configuration is being read at the device CLI during deployment. Do not execute commands such as **show running-config** during the deployment.

Procedure

Step 1 In the Cloud-Delivered Firewall Management Center menu bar, click **Deploy**.


Step 2 For a quick deployment, check specific devices and then click **Deploy**, or click **Deploy All** to deploy to all devices. For additional deployment options, click **Advanced Deploy**.

You can run a Pre-deployment Assessment to proactively verify your environment's runtime readiness and policy configurations, before deployment. Click the **Pre-deployment Assessment** link to perform two types of pre-deployment assessments:

- **Basic assessment**
- **Advanced assessment**


For more information about these assessments, refer to Pre-deployment assessments, on page 20.

Figure 1: Quick Deploy



The rest of this procedure applies to the **Advanced Deploy** screen.

Figure 2: Advanced Deployment



Step 3 Click **Expand Arrow** (>) to view device-specific configuration changes to be deployed.

- The **Modified By** column lists the users who have modified the policies or objects. On expanding the device listing, you can view the users who have modified the policies against each policy listing. For information about when the **System** user is shown (instead of the logged-in user), refer to System username, on page 5.

Note Usernames are not provided for deleted policies and objects.

- The **Inspect Interruption** column indicates if traffic inspection interruption may be caused in the device during deployment.

  When the status indicates (Yes) that deploying will interrupt inspection, and perhaps traffic, on the Firewall Threat Defense device, the expanded list indicates the specific configurations causing the interruption with the **Inspect Interruption** (</>).

  If the entry is blank in this column for a device, then it indicates that there will be no traffic inspection interruptions on that device during deployment.

  For information about identifying configurations that interrupt traffic inspection and might interrupt traffic when deployed to the Firewall Threat Defense devices, refer to Inspection interruption warnings during deployment, on page 7.

- The **Last Modified Time** column specifies when you last made the configuration changes.
- The **Preview** column allows you to preview the changes for the next deployment.
- The **Status** column provides the status for each deployment. For more information, see Deployment status, on page 24.


Step 4 In the **Preview** column, click **Preview** ( ) to see the configuration changes that you can deploy.

Note If you change the Cloud-Delivered Firewall Management Center name in **Administration** > **Configuration** > **Information** , the deployment preview does not specify this change, yet it requires a deployment.

For unsupported features for Preview, see Deployment preview, on page 2.

The **Comparison View** tab lists all the policy and object changes. The left pane lists all the different policy types that have changed on the device, organized in a tree structure.

Figure 3: Comparison View



The **Filter**( ) lets you filter the policies at the user level and policy level.


The right pane lists all the additions, changes, or deletions in the policy, or the object selected in the left pane. The two columns on the right pane provide the last deployed configuration settings (in the **Deployed Version** column) versus the changes that are due for deployment (in the **Version on Firewall Management Center** column). The last-deployed configuration settings are derived from a snapshot of the last saved deployment in the Cloud-Delivered Firewall Management Center and not from the device. The background colors of the settings are color-coded as per the legend available on the top-right of the page.

The **Modified By** column lists the users who have modified, or added the configuration settings. At the policy level, the Cloud-Delivered Firewall Management Center displays all the users who have modified the policy, and at the rule level, the Cloud-Delivered Firewall Management Center displays only the last user who has modified the rule.

You can download a copy of the change log by clicking the **Download Report** button.


The **Advanced View** tab shows the CLI commands that will be applied. This view is useful if you are familiar with ASA CLI, which is used on the back end of the Firewall Threat Defense.

Figure 4: Advanced View



Step 5 Use **Show or Hide Policy** ( ) to selectively view or hide the associated unmodified policies.

Figure 5: Show or Hide Policy



Step 6 Check the box next to the device name to deploy all configuration changes, or click **Policy selection** ( ) to select individual policies or configurations to deploy while withholding the remaining changes without deploying them.

You can also view the interdependent changes for a certain policy or configuration using this option. The Cloud-Delivered Firewall Management Center dynamically detects dependencies between policies (for example, between an access control policy and an intrusion policy), and between the shared objects and the policies. Interdependent changes are indicated using color-coded tags to identify a set of interdependent deployment changes. When one of the deployment changes is selected, the interdependent changes are automatically selected.

For more information, refer to Guidelines for selective policy deployment, on page 3.

Note

- When the changes in shared objects are deployed, the impacted policies should also be deployed along with them. When you select a shared object during deployment, the impacted policies are automatically selected.
- Selective deployment is not supported for scheduled deployments and deployments using REST APIs. You can only opt for complete deployment of all the changes in these cases.
- The pre-deployment checks for warnings and errors are performed not only on the selected policies, but on all the policies that are out-of-date. Therefore, the warnings or errors list shows the deselected policies as well.
- Similarly, the **Inspect Interruption** column indication on the Deployment page considers all out-of-date policies and not just the selected policies. For information on the **Inspect Interruption** column, refer to Inspection interruption warnings during deployment, on page 7.

Step 7 After you select the devices or policies to deploy, click **Estimate** to get a rough estimate of the deployment duration .

Figure 6: Estimate





Figure 7: Deploy Time



The time duration is a rough estimate (having around 70% accuracy), and the actual time taken for deployment may vary for a few scenarios. The estimate is dependable for deployments of up to 20 devices.

When an estimate is not available, it indicates that the data is not available, since the first successful deployment on the selected device is pending. This situation could occur after the Cloud-Delivered Firewall Management Center reimage, version upgrade, or after a high availability failover.

Note The estimate is incorrect and unreliable for bulk policy changes (in case of bulk policy migrations), and selective deployments because the estimate is based on the heuristic technique.

Step 8 For more details about the Pre-readiness assessment states, refer to .

Step 9 Click **Deploy**.

Configuration changes are deployed to the selected devices. You receive confirmation messages regarding success, warnings, or errors.

What to do next

If the system identifies errors or warnings in the changes to be deployed, it displays them in the **Validation Messages** window. To view complete details, click the arrow icon before the warnings or errors.

You have the following choices:

- Deploy—Continue deploying without resolving warning conditions. Check the **Ignore warnings** checkbox, to ignore warnings and deploy the changes. You cannot proceed if the system identifies errors.
- Close—Exit without deploying. Resolve the error and warning conditions, and attempt to deploy the configuration again.
- (Optional) Monitor deployment status; see *Viewing Deployment Messages* in the *Cisco Secure Firewall Management Center Administration Guide* .
- If the deployment fails, refer to Best practices for deploying configuration changes, on page 12 .
- During deployment, if there are specific configuration changes in the deployment, the deployment failure may lead to traffic being interrupted. For example, in a cluster environment, an erroneous configuration of an IP address that is not in the same subnet as the Site IPs is configured on the interface. Due to this error, deployment fails and the device attempts to clear the configuration while the rollback operation is being processed. These events collectively lead to a deployment failure that interrupts the traffic.

  See the following table to know what configuration changes may cause traffic interruption when deployment fails.

Table 5: Traffic interruption scenarios

Configuration Changes	Exists?	Traffic Impacted?
Threat Defense Service changes in an access control policy	Yes	Yes
VRF	Yes	Yes
Interface	Yes	Yes
QoS	Yes	Yes



Note The configuration changes interrupting traffic during deployment is valid only if both the Cloud-Delivered Firewall Management Center and the Firewall Threat Defense are of version 6.2.3 or later.

Pre-deployment assessments

In the Cloud-Delivered Firewall Management Center menu bar, click **Deploy** to run pre-deployment assessments. You can run pre-deployment assessments to proactively verify your environment's runtime readiness and policy configurations, before deployment. These assessments help you remediate issues before they cause network outages or security incidents.

Click **Pre-deployment Assessment** in the Quick Deploy banner to perform two types of pre-deployment assessments:

- **Basic assessment**
- **Advanced assessment**

Basic assessment

This assessment runs rule-based checks to identify blockers and misconfigurations, including policy, device, runtime, dependency, and certificate expiration risks, before deployment. It validates your configurations and reports the status of each check. Use the details in the assessment report to remediate any issues found.

To run basic assessment on a Firewall Threat Defense device:

1. In the Cloud-Delivered Firewall Management Center menu bar, click **Deploy**.
2. Click **Pre-deployment Assessment** in the banner or **Advanced Deploy**.
3. In the **Advanced Deployment** screen, select one or more devices.
4. Choose **Run Assessments > Basic Assessments**.

   You can view the state of the assessments, and click **View report** to view the Assessment report. This report displays a summary of the findings, groups them by severity, and provides the description, component, cause, and recommended remediation for each issue.

Advanced assessment

This assessment uses AI to analyze your firewall policies and evaluate their risk profile before you deploy them on the Firewall Threat Defense devices. It provides deeper insights into how the changes might impact your network, allowing you to review and fine-tune your policies before deployment.

Advanced Assessment compares the last deployed access control policy with the proposed policy, including saved changes that are pending deployment.

The assessment identifies traffic whose effective policy decision would change, such as traffic that becomes allowed or blocked. When historical connection events are available, the assessment also shows observed traffic that matches the affected traffic segments.

Use the assessment results to:

- Review affected rules and traffic.
- Confirm that the result matches the intended policy change.
- Revise and rerun the assessment, if needed.

Running an assessment does not change or deploy the policy.

Note To run the advanced assessments, you must enable the Policy Change Impact Analyzer in Security Cloud Control. Choose **Insights & Reports > Settings**.

When you run this assessment, it automatically performs two checks:

1. Basic assessment
2. AI-based assessment using Policy Change Impact Analyzer.

To run an advanced assessment on a Firewall Threat Defense device:

1. In the Cloud-Delivered Firewall Management Center menu bar, click **Deploy**.
2. Click **Pre-deployment Assessment** in the banner or **Advanced Deploy**.
3. In the **Advanced Deployment** screen, select one or more devices.
4. Choose **Run Assessments > Advanced Assessments**.

   Cloud-Delivered Firewall Management Center starts the assessment. Policy Impact Analyzer evaluates the saved, pending access control policy changes for each eligible device.

   Monitor the state of the assessments, and click **View report** to view the Assessment report. This cross-launches the Policy Change Impact Analyzer page for the selected Firewall Threat Defense device, where you can review the result and supporting details.

Related information

- Understand Policy Change Impact Analyzer results, on page 22
- Review the Advanced Assessment report, on page 22
- About policy change impact insights

Understand Policy Change Impact Analyzer results

The **Analysis Result** summarizes the combined effect of the pending access control policy changes for advice. The result is displayed in the Cloud-Delivered Firewall Management Center Advanced Deploy page after the analysis.

Note Assessment state and Analysis Result are different. The state indicates whether processing is queued, in progress, completed, or unsuccessful.

Analysis Result describes the impact determined for the pending policy changes.

Table 6:

Analysis Result	Description	Recommended Action
Critical	One or more changes may expose the network to threats or disrupt services.	Review the affected rules and traffic segments before deployment. If the change is unintended, revise the policy and rerun Advanced Assessment.
Potential Impact	One or more changes expand access or may affect traffic.	Validate the affected traffic and expected business outcome before deployment.
Improved Security Posture	One or more changes reduce exposure or block risky traffic.	Confirm that the affected traffic is intentionally restricted, and then continue through the normal change-review process.
No Traffic Impact	No behavior-changing traffic transition was identified by comparing the deployed and proposed policies.	Confirm that the proposed rule is needed and positioned as intended. This result is different from a change that has zero observed connections.
Indeterminate	The available evidence was insufficient to determine a reliable impact.	Review the changed rule and traffic criteria manually. Gather additional operational context and rerun the assessment when appropriate.

Review the Advanced Assessment report

Use the report to review the overall result, affected access control rules, traffic decision transitions, and available historical connection evidence.

Historical connection counts show traffic observed during the available lookback period; they are not a forecast of future traffic.

- Confirm each intended block-to-allow and allow-to-block transition.
- Review affected rules and traffic segments before deciding to deploy.

- Do not treat zero observed connections as proof that a policy change has no risk.
- Rerun Advanced Assessment after changing the pending policy.
- Use the result as decision-support evidence; the policy owner remains responsible for the deployment decision.

Redeploy existing configurations to a device

Force-deploying existing configurations to a managed device ensures that its policy rules are fully regenerated and applied. This procedure is recommended during maintenance windows or when disruption to network traffic is minimal. Force-deploy takes longer than regular deployment because it generates all policy rules for the device.

Caution When you deploy, resource demands may result in a small number of packets dropping without inspection. Additionally, deploying some configurations restarts the Snort process, which interrupts traffic inspection. Whether traffic drops during this interruption or passes without further inspection depends on how the target device handles traffic. Refer to Snort restart traffic behavior, on page 8 and Configurations that restart the snort process when deployed or activated, on page 10.

Before you begin

- Review the guidelines described in Best practices for deploying configuration changes, on page 12.
- Plan to perform the redeployment during a maintenance window or low-impact period.

Procedure

Step 1 Choose **Devices** > **Device Management**.

Step 2 Click **Edit** (✎) next to the device where you want to force deployment.

Step 3 Click **Device**.

Step 4 Click **Edit** (✎) next to the **General** section heading.

Step 5 Click **Force Deploy** (→).

Step 6 Click **Deploy**.

The system identifies any errors or warnings with the configurations you are deploying. You can click **Proceed** to continue without resolving warning conditions. However, you cannot proceed if the system identifies an error.

What to do next

- (Optional) Monitor deployment status; see *Viewing Deployment Messages* in the *Cisco Secure Firewall Management Center Administration Guide*.
- If deploy fails, see Best practices for deploying configuration changes, on page 12.

Deployment management

Cloud-Delivered Firewall Management Center provides a set of deployement management options to oversee configuration changes across your Firewall Threat Defense devices. These options enable you to monitor real-time deployment status, track historical records, and ensure configuration integrity through rollback capabilities. Additionally, you can utilize built-in reporting and policy comparison features to audit changes, verify compliance, and troubleshoot issues.

Deployment status

On the **Deployment** page, the **Status** column provides the deployment status for each device. If a deployment is in progress, a live progress indicator is displayed; otherwise, one of these deployment status values appears:

- **Pending**: Indicates that there are changes in the device that need be deployed.
- **Warnings or errors**: Indicates that the pre-deployment checks have identified warnings or errors for the deployment. You may continue deployment if there are warnings, but not if there are errors.

Note The status column provides the warning or error status only for a single user session on the **Deployment** page. If you navigate away or refresh the page, the status changes to **Pending**.

- **Failed**: Indicates that the previous deployment attempt failed. Click the status to view the details.
- **In queue**: Indicates that deployment is initiated, and the system is yet to start the deployment process.
- **Completed**: Indicates that deployment has completed successfully.

View deployment history


View deployment history to track and analyze past deployment activities, including successful deployments, failed deployments, and rollback operations.

In the deployment history, the last 10 successful deployments, the last 5 failed deployments, and last 5 rollback deployments are captured.

Procedure


Step 1 On the Cloud-Delivered Firewall Management Center menu bar, click **Deploy** and then click **Deployment History** ( ).

Figure 8: Deployment history icon




A list of all the previous deployment and rollback jobs is displayed in reverse chronological order.

Figure 9: Deployment history page



Step 2 Click **Expand Arrow** (>) next to the required deployment job to view the devices included in the job and their deployment statuses.

Figure 10: Expand



- View notes in the **Deployment Notes** column.

  Deployment notes are custom notes that a user can add as part of the deployment, and these notes are optional.

Step 3 (Optional) Click **Transcript Details** ( ) to view the commands sent to the device, and the responses received.

Figure 11: Transcript details icon





Figure 12: Transcript details



The transcript includes the following sections:

- **Snort Apply**—If there are any failures or responses from Snort-related policies, then the messages are displayed in this section. Normally, the section is empty.
- **CLI Apply**—This section covers features that are configured using commands that are sent to the device.
- **Infrastructure Messages**—This section shows the status of different deployment modules.

In the **CLI Apply** section, the deployment transcript includes commands that are sent to the device, and any responses returned from the device. These responses can be informative messages or error messages. For failed deployments, look for messages that indicate errors with the commands. Examining these errors can be particularly helpful if you are using FlexConfig policies to configure customized features. These errors can help you correct the script in the FlexConfig object that is trying to configure the commands.

Note There is no distinction that is made in the transcript between commands that are sent for managed features and those generated from FlexConfig policies.


For example, the following sequence shows that Cloud-Delivered Firewall Management Center sent commands to configure GigabitEthernet0/0 with the logical name **outside**. The device responded that it automatically set the security level to 0. Firewall Threat Defense does not use the security level for anything.

```
========= CLI APPLY =========

FMC >> interface GigabitEthernet0/0
FMC >>  nameif outside
FTDv 192.168.0.152 >> [info] : INFO: Security level for "outside" set to 0 by default.
```


Step 4 (Optional) Click **Preview** ( ) to view the policy and object changes deployed on the device versus the previously deployed version.

Figure 13: Preview icon



a. To compare any two versions and view the change log, choose the required versions in the drop-down boxes and click the **Show** button. The drop-down boxes show the deployment job name and the end time of the deployment.

Figure 14: Compare versions



Note The drop-down boxes also show failed deployments.

b. The **Modified By** column lists the users who have modified the policies or objects.

1. At the policy level, Cloud-Delivered Firewall Management Center displays all the user names who have modified the policy.
2. At the rule level, Cloud-Delivered Firewall Management Center displays the last user who has modified the rule.

c. You can also download a copy of the change log by clicking **Download Report**.

Note


- Deployment history preview is not supported for certificate enrollments, HA operations, and failed deployments.
- When a device is registered, preview is not supported for the job history record that is created.

Step 5 (Optional) Against each deployment job, click the **More** (⋮) icon and execute other actions:

- **Bookmark**—To bookmark the deployment job.
- **Edit Deployment Notes**—To edit your custom deployment notes that you added for a deployment job.
- **Generate Report**—To generate a deployment report, which can be used for auditing. This report includes job properties with preview and transcript information, and the report can be downloaded as a PDF file.

  a. Click **Generate Report** to generate a deployment report.

  Figure 15: Generate report

  b. In the **Generate Report** popup window, check the **Email** checkbox.

  c. In the **Recipient List**, you can enter multiple email adddresses, separated by semicolons.

  d. Click **Generate** to generate the report, and this report is emailed to the recipients.

  e. In the Notifications task tab, you can track the progress. After the report generation is complete, click the link in the notification task tab to download the PDF report.

Deployment rollback

Deployment rollback is the process of reverting a device to a previously saved configuration state. This operation allows you to restore the device to its earlier state if a recent policy deployment results in unintended traffic behavior.

Note Rollback is a disruptive operation. Executing a rollback terminates all existing connections and resets routing tables, which will cause a temporary interruption of traffic.

Identifying the disruptive configuration

When a deployment has caused unintended traffic interruption, identify the specific change responsible for the condition. To compare current and previous deployments:

Before a rollback

1. Choose **Deploy** > **Deployment History**, expand the last deployed job that caused the traffic disruption, and click the **Preview** ( ).

   The preview page lets you compare deployments to identify specific changes from previous configurations.

2. After identifying the change causing the problem, rectify the configuration and redeploy it on the device.

After a rollback

1. After a successful rollback, choose **Deploy** > **Deployment**, and click the **Preview** icon next to the rolled back device.
2. View the changes between the rolled back configuration and the current changes in the Cloud-Delivered Firewall Management Center that are pending deployment.
3. After identifying the change causing the problem, rectify the configuration, and redeploy it on the device.

Rollback reverts most configurations, but some exceptions apply. Refer the table below for details.

Rollback guidelines

Follow these guidelines to ensure successful configuration rollbacks.

- You have to perform a deployment before you can roll back again.
- After you perform a rollback, the rolled back devices are marked as out-of-date on the Cloud-Delivered Firewall Management Center. The changes you made to the configuration are still pending for the next deployment. To see the pending changes, choose **Deploy** > **Deployment**, and click the **Preview** icon next to the rolled back device.
- For devices with very large access lists, if the **Object Group Search** setting is disabled, then the rollback operation may take a longer duration to complete. To verify the **Object Group Search** setting, choose **Devices** > **Device Management**, and then select the device and click **Edit Advanced Settings**.
- For the Firepower 4100/9300, make sure your current Firewall Chassis Manager interface configuration is the same for any rollback versions. Otherwise, the rollback interface configuration may not match your actual interfaces.

- Independent certificate enrollments are also listed as deployment jobs in the Deployment History page. However, you cannot roll back to these versions. A rollback from a deployment version created after certificate enrollments reverts the certificate associations as well. In the next deployment after a rollback, manually associate the certificates before proceeding with the deployment.
- If a deployment for a device with a FlexConfig object configured with a deployment frequency set to **Once** is rolled back, then you will not be able to redeploy the object even though it is displayed as out-of-date on the Preview page. After a rollback, you will have to manually unassign and then reassign the FlexConfig object to the device before the next deployment.

Rollback limitations

Observe these limitations that restrict the use of rollback functionality.

- You can roll back to any one of the last 10 versions before the currently deployed version. Rollback to versions prior to these are not supported. The rollback icon is greyed out for unsupported versions.
- Rollback is not supported if the manager access interface (Manager or data interface) is different between the rollback version and the current version.
- If you upgrade the Cloud-Delivered Firewall Management Center, all rollback versions from the previous software release will no longer be available for devices, even if you did not upgrade the devices.
- If you upgrade the device, you can only roll back to versions on the current software release.
- For High Availability, rollback is not supported in these scenarios:
  - When the version you want to roll back to contains the high-availability bootstrap configuration. In other words, the deployment when you first formed high availability for the standalone devices.
  - When a device that is currently in standalone mode was part of a high availability pair in the previous deployment version.
- For clustering:
  - Rollback is not supported when a device that is currently in standalone mode was part of a cluster in the previous deployment version.
  - (Secure Firewall 3100/4200 and Firewall Threat Defense Virtual in a private cloud) If you change the clustering bootstrap configuration or add or delete nodes, you cannot roll back to a version prior to those changes.

Table 7: Configurations reverted and not reverted during rollback

Configurations that are reverted during a rollback	Configurations that are not reverted during a rollback
• All policy configurations • Interface configurations • SRU configurations • VDB configurations • LSP configurations • VPN configurations • FXOS configurations	• Snort binaries • Geo DB

Perform a rollback

Use rollback to revert a device to a previously deployed configuration when the traffic through the device is affected in an unintended way after a policy deployment.

You can roll back a device to a previously deployed configuration. After a policy deployment, if the traffic through the device is affected in an unintended way, rollback provides an option to revert the device to the earlier state, which existed before the faulty deployment.

Rollback reverts the configuration only on the selected devices.

Procedure

Step 1 Choose **Deploy >Deployment History** ( ).

A list of all the previous deployment jobs is displayed in reverse chronological order.

Step 2 Click **Rollback**.

Step 3 Filter the list of devices displayed by either clicking **Job** and choosing a job from the **Selected Job** drop-down list, or by clicking **Device List**.

Step 4 (Optional) Enter the device name in the **Search Device** search box to filter the device list.

Step 5 Check the box next to the devices you want to roll back and choose the version for each device from the **Rollback Version** drop-down list.

Figure 16: Selected job list





Figure 17: Device list



The job names and associated deployment notes are also listed for a particular rollback version.

Step 6 (Optional) Click the **Preview** ( ) to view the changes deployed in the selected version.

Step 7 Click **Rollback** to restore the selected devices to the chosen configuration version.

What to do next

To verify rollback status, go to **Deploy** > **Deployment** and check the rollback status next to the device name.

View the deployment rollback transcript

View the CLI commands that were executed during a successful rollback operation to understand what changes were made to the device configuration.

Rollback transcript is a written version of the commands that are sent to the device, along with the responses returned from the device. If a rollback operation has failed, the reason for the failure can be viewed by clicking **Deploy**, and then click the **Deployment History** (). However, to know the CLI commands executed for a successful rollback operation, follow the steps given below after a rollback operation has completed.

Note

- The CLI command information is available after a rollback is complete and is available only until the next deployment. The first deployment after a rollback operation erases all the rollback-related information.
- For any rollback deployment, the deployment notes are updated automatically as rollback job. In the **Deployment History** page, the user can filter the rollback jobs easily using the search option.

Procedure

Step 1 On the Cloud-Delivered Firewall Management Center menu bar, choose **Troubleshooting** > **Health** > **Monitor**.

Step 2 Select the device, which was rolled back, from the left pane.

Step 3 Click **View System & Troubleshooting Details** link.

Step 4 Click **Advanced Troubleshooting**.

Step 5 Click **Threat Defense CLI**.

Step 6 Select **show** from the **Command** drop-down box.

Step 7 Enter `running` in the **Parameter** field.

Step 8 Click **Execute**.

Download policy changes report for multiple devices

Download reports on the policy and object changes made since your last deployment for multiple Firewall Threat Defense devices. Reports help you review pending changes before completing deployment. The reports are provided as a zip file containing:

- A pending changes report for each device, previewing modifications to policy or objects that are to be deployed on the device. For more information, refer to Deploy configuration changes, on page 14 and Deployment Preview.
- A consolidated report categorizing each device by report status.

Procedure

Step 1 Choose **Deploy** > **Advanced Deploy**.

Step 2 Check the check box next to the devices for which you want to generate a pending policy changes report, and then click **Pending Changes Reports**.

Step 3 Click **Pending Changes Reports**. Reports are generated in the background.

Step 4 On the Cloud-Delivered Firewall Management Center menu bar, choose **Notifications** > **Tasks** to view the report generation task.

When the report request task is complete, the download link appears within the task notification.

Step 5 Click the **Download Report(s)** link to download the reports.

Compare policies

Policy comparison allows you to examine the differences between two policies or between a saved policy and the running configuration to review policy changes for compliance with your organization's standards or to optimize system performance.

You can compare these policy types:

- DNS
- File
- Health
- Identity
- Network Analysis
- SSL

The comparison view displays both policies in a side-by-side format. Differences between the two policies are highlighted:

- Blue indicates that the highlighted setting is different in the two policies, and the difference is noted in red text.
- Green indicates that the highlighted setting appears in one policy but not the other.

Before you begin

You can compare policies only if you have access rights and any required licenses for the specific policy, and you are in the correct domain for configuring the policy.

Procedure

Step 1 Access the management page for the policy you want to compare:

- DNS—**Policies** > **Security policies** > **DNS**
- File—**Policies** > **Security policies** > **Malware & File**
- Health—**Troubleshooting** > **+ Show more** > **Health** > **Policies**
- Identity—**Policies** > **Security policies** > **Identity**

- Network Analysis—**Policies** > **Security policies** > **Access Control**, and then click **Network Analysis Policy** or **Policies** > **Security policies** > **Intrusion**, and then click **Network Analysis Policies**.

Note If your custom user role limits access to the first path listed here, use the second path to access the policy.

- SSL—**Policies** > **Security policies** > **Decryption**

Step 2 Click **Compare Policies**.

Step 3 From the **Compare Against** drop-down list, choose the type of comparison you want to make:

- To compare two different policies, choose **Other Policy**.
- To compare two revisions of the same policy, choose **Other Revision**.
- To compare another policy to the currently active policy, choose **Running Configuration**.

Step 4 Depending on the comparison type you choose, you have various choices:

- If you are comparing two different policies, choose the policies you want to compare from the **Policy A** and **Policy B** drop-down lists.
- If you are comparing the running configuration to another policy, choose the second policy from the **Policy B** drop-down list.

Step 5 Click **OK**.

Step 6 Review the comparison results:

- Comparison Viewer—To use the comparison viewer to navigate individually through policy differences, click **Previous** or **Next** above the title bar.
- Comparison Report—To generate a PDF report that lists the differences between the two policies, click **Comparison Report**.

Generate current policy reports

You can generate two types of reports for most policies: a single-policy report detailing the policy's current saved configuration, and a comparison report listing differences between two policies. You can generate a single-policy report for all policy types except health.

Note Intrusion policy reports combine the settings in the base policy with the settings of the policy layers, and make no distinction between which settings originated in the base policy or policy layer.

Before you begin

- Ensure you have the required access rights and licenses for the specific policy.
- Verify you are operating within the correct domain for the policy you wish to report.

Procedure

Step 1 Access the management page for the policy for which you want to generate a report:

- Access Control—**Policies** > **Security policies** > **Access Control**
- DNS—**Policies** > **Security policies** > **DNS**
- File—**Policies** > **Security policies** > **Malware & File**
- Health—**Troubleshooting** > **+ Show more** > **Health** > **Policies**
- Identity—**Policies** > **Security policies** > **Identity**
- Intrusion—**Policies** > **Security policies** > **Intrusion**
- NAT—**Policies** > **Network policies** > **NAT**
- Network Analysis—**Policies** > **Security policies** > **Access Control**, and then click **Network Analysis Policy** or **Policies** > **Security policies** > **Intrusion**, and then click **Network Analysis Policies**



Note If your custom user role limits access to the first path listed here, use the second path to access the policy.

- SSL—**Policies** > **Security policies** > **Decryption**

Step 2 Click **Report** () next to the policy for which you want to generate a report.