Release Notes for Cisco Catalyst IE9300 Rugged Series Switches, Cisco IOS XE 17.17.x

First Published: 2025-03-31

Information about Cisco Catalyst IE9300 Rugged Series Switch

This document provides release information for the following Catalyst IE switches:

- Cisco Catalyst IE9310 GE Fiber switch
- Cisco Catalyst IE9320 GE Fiber switch
- Cisco Catalyst IE9320 Fiber switch with 10 GE uplinks
- Cisco Catalyst IE9320 10 GE Copper Data switch
- Cisco Catalyst IE9320 10 GE PoE switch
- Cisco Catalyst IE9320 10 G mGig 4PPoE switch
- Cisco Catalyst IE9320 GE PoE switch

Cisco Catalyst IE9300 Rugged Series Switches provide rugged and secure switching infrastructure for harsh environments. They are suitable for industrial Ethernet applications, including manufacturing, utility substations, intelligent transportation systems (ITSs), rail transportation, and other similar deployments.

The switch fulfills the need for a high-density SFP, RJ-45, and Power over Ethernet (PoE) rack- or wall-mounted switch that can function as a software-defined access (SD-Access) fabric edge. It provides end-to-end architectural uniformity in the Cisco Catalyst Center for Internet of Things (IoT) connected communities and extended enterprises.

In industrial environments, the switch can be connected to any Ethernet-enabled industrial communication devices. These devices include programmable logic controllers (PLCs), human-machine interfaces (HMIs), drives, sensors, and input and output (I/O) devices.

New Features in Release 17.17.1

Feature Name	License Level	Description	Supported Platforms	Related Document
Media Redundancy Protocol on an IE9300 Stack	Network Essentials and Network Advantage	From this release, stack support for Media Redundancy Protocol (MRP) is introduced.	IE9300	Redundancy Protocol Configuration Guide

Switch Model Numbers

Cisco Catalyst IE9300 Rugged Series Switches

The following table lists the supported IE9300 series hardware models and the default license levels that they are delivered with.

Model Number	Default License Level	Stacking Support	Description
IE-9310-26S2C-A	Network Advantage	No	• *Total ports*: 28 • *SFP uplinks*: 4x 1 Gb SFP *SFP downlinks*: 22x 100M/1000M SFP, 2x 100M/1000M dual-media • *Power supplies*: Support for field-replaceable, redundant AC or DC power supplies
IE-9310-26S2C-E	Network Essentials		
IE-9320-26S2C-A	Network Advantage	Yes	• *Total ports*: 28 • *SFP uplinks*: 4x 1 Gb SFP *SFP downlinks*: 22x 100M/1000M SFP, 2x 100M/1000M dual-media • *Power supplies*: Support for field-replaceable, redundant AC or DC power supplies
IE-9320-26S2C-E	Network Essentials		

Model Number	Default License Level	Stacking Support	Description
IE-9320-22S2C4X-A	Network Advantage	Yes	• *Total ports*: 28 • *SFP uplinks*: 4x 10 Gb SFP+ • *SFP downlinks*: 22x 1 Gb SFP, 2x 1-Gb Dual-media ports • *Power supplies*: Support for field-replaceable, redundant AC or DC power supplies
IE-9320-22S2C4X-E	Network Essentials		
IE-9320-24T4X-A	Network Advantage	Yes	• *Total ports*: 28 • *SFP uplinks*: 4x 10 Gb SFP+ • *Copper downlinks*: 24x 1 Gb RJ45 • *Power supplies*: Support for field-replaceable, redundant AC or DC power supplies.
IE-9320-24T4X-E	Network Essentials		
IE-9320-24P4X-A	Network Advantage	Yes	• *Total ports*: 28 • *SFP uplinks*: 4x 10 Gb SFP+ • *Copper downlinks*: 24x 1 Gb RJ45 PoE+ • *Power supplies*: Support for field-replaceable, redundant AC or DC power supplies
IE-9320-24P4X-E	Network Essentials		

Model Number	Default License Level	Stacking Support	Description
IE-9320-16P8U4X-A	Network Advantage	Yes	• *Total ports*: 28 • *SFP uplinks*: 4x 10 Gb SFP • *Copper downlinks*: 16 ports 1 Gb RJ45 PoE+, 8 ports 2.5 Gb RJ45 4PPoE (90W/port) • *Power supplies*: Support for field-replaceable, redundant AC or DC power supplies
IE-9320-16P8U4X-E	Network Essentials		
IE-9320-24P4S-A	Network Advantage	Yes	• *Total ports*: 28 • *SFP uplinks*: 4x 1Gb SFP • *Copper downlinks*: 24 ports 1 Gb RJ45 PoE+ • *Power supplies*: Support for field-replaceable, redundant AC or DC power supplies
IE-9320-24P4S-E	Network Essentials		

All Cisco Catalyst IE9300 Rugged Series Switches have 4 GB of DRAM, four alarm inputs, and one alarm output. Other I/O interfaces include the following:

- SD cards slot
- Power input
- RJ-45 (RS-232) console
- Micro-USB console
- USB-A host port

Note Documentation sometimes uses the following terms:

- IE9310 GE Fiber switch when referring to both IE-9310-26S2C-A and IE-9310-26S2C-E switches
- IE9320 GE Fiber switch when referring to both IE-9320-26S2C-A and IE-9320-26S2C-E switches
- IE9320 Fiber switch with 10 GE uplinks when referring to both IE-9320-22S2C4X-A and IE-9320-22S2C4X-E switches
- IE9320 10 GE Copper Data switch when referring to both IE-9320-24T4X-A and IE-9320-24T4X-E switches
- IE9320 10 GE PoE switch when referring to both IE-9320-24P4X-A and IE-9320-24P4X-E
- IE9320 10 G mGig 4PPoE switch when referring to both IE-9320-16P8U4X-A and IE-9320-16P8U4X-E
- IE9320 GE PoE switch when referring to both IE-9320-24P4S-A and IE-9320-24P4S-E

Starting with release 17.10.1, both the Network Essentials license and the Network Advantage license are available. The features available in the two licenses follow the IE9300 series, with the exception of MACsec-256.

Network Advantage License	Description
Security	MACsec-256
Routing	Layer 3 routing support

Upgrading the Switch Software

This section covers the various aspects of upgrading or downgrading the device software.

Note See the Cisco IOS XE Migration Guide for IIoT Switches for the latest information about upgrading and downgrading switch software.

SSH Algorithms for Common Criteria Certification Limitation

Starting with Cisco IOS XE Release 17.10, the following Key Exchange and MAC algorithms are removed from the default list:

- Key Exchange algorithm:
  - diffie-hellman-group14-sha1
- MAC algorithms:
  - hmac-sha1
  - hmac-sha2-256

- hmac-sha2-512

Note You can use the **ip ssh server algorithm kex** command to configure the Key Exchange algorithm and the **ip ssh server algorithm mac** command to configure the MAC algorithms.

Alarm relay polarity changes

Note Starting with Cisco IOS XE Release 17.17.1, the **alarm relay-mode** command aligns the positive and negative relay states with the polarity of the physical alarm output pins. This behavior differs from earlier releases. After an upgrade, verify the alarm relay configuration and external wiring to ensure that alarm and no-alarm conditions operate as expected.

```
Switch# show alarm settings | in alarm relay mode
Alarm relay mode: Positive
```

Finding the Software Version

The package files for Cisco IOS XE software can be found on the system board's internal flash memory device (flash:) or an external USB, depending on the device configuration.

You can use the **show version** privileged EXEC command to see the software version that is running on your switch.

Note Although the **show version** output always shows the software image running on the switch, the model name shown at the end of this display is the factory configuration and does not change if you upgrade the software license.

You can also use the **dir** *filesystem:* privileged EXEC command to see the names and versions of other software images that you might have stored in flash memory.

Software Images for Cisco IOS XE 17.17.x

The following table provides the filename for the IOS XE 17.17.x software image for Cisco Catalyst IE9300 Rugged Series Switches.

Release	Image Type	Filename	Switch Models
Cisco IOS XE.17.17.1	Universal	ie9k_iosxe.17.17.01.SPA.bin	Cisco Catalyst IE9300 Rugged Series Switches

Software Installation Options

The following table lists the options for the **install** command for Cisco Catalyst IE9300 Rugged Series Switches.

To install and activate the specified file, and to commit changes to be persistent across reloads, enter the following command: **install add file** *filename* [**activate commit**]

Option	Description
abort	Abort the current install operation.
activate	Activate an installed package.
add	Install a package file to the system.
auto-abort-timer	Install auto-abort-timer.
autoupgrade	Initiate software auto-upgrade on all incompatible switches.
commit	Commit the changes to the load path.
deactivate	Deactivate an install package.
label	Add a label name to any installation point.
remove	Remove installed packages.
rollback	Rollback to a previous installation point.

Licensing

For information about the licensing packages for features available on Cisco Catalyst IE9300 Rugged Series Switches and Cisco Catalyst ESS9300 Embedded Series Switch, see Licensing on the Cisco Catalyst IE9300 Series Switches.

License Levels

The software features available on Cisco Catalyst IE9300 Rugged Series Switches fall under these base or add-on license levels.

Base Licenses

- Network Essentials
- Network Advantage: Includes features available with the Network Essentials license and more.

Add-on Licenses

Add-on licenses require a Network Essentials or Network Advantage as a prerequisite. The features available with add-on license levels provide Cisco innovations on the switch, and on the Cisco Catalyst Center.

- Catalyst Center DNA Essentials
- Catalyst Center DNA Advantage: Includes features available with the Catalyst Center DNA Essentials license and more.

To find information about platform support and to know which license levels a feature is available with, use Cisco Feature Navigator. To access Cisco Feature Navigator, go to https://cfnng.cisco.com. An account on Cisco.com is not required.

Smart Licensing Using Policy

Smart Licensing Using Policy, which is an enhanced version of Smart Licensing, is the default and the only supported method to manage licenses.

Smart Licensing Using Policy provides a licensing solution that does not interrupt the operations of your network. Instead, it enables a compliance relationship to account for the hardware and software licenses you purchase and use.

With this licensing model, you do not have to complete any licensing-specific operations, such as registering or generating keys before you start using the software and the licenses that are tied to it. Only export-controlled and enforced licenses require Cisco authorization *before* use. License usage is recorded on your device with timestamps, and the required workflows can be completed later.

Multiple options are available for license-usage reporting. The available options depend on the implemented topology. You can use the Cisco Smart Licensing Utility (CSLU) Windows application, or report usage information directly to Cisco Smart Software Manager (CSSM). A provision for offline reporting for air-gapped networks, where you download usage information and upload to CSSM, is also available.

Starting with this release, Smart Licensing Using Policy is automatically enabled on the device. This is also the case when you upgrade to this release.

By default, your Smart Account and Virtual Account in CSSM are enabled for Smart Licensing Using Policy.

Caveats

Caveats describe unexpected behavior in Cisco IOS XE releases.

Open Caveats in Cisco IOS XE 17.17.x

Identifier	Description
CSCwo52580	IE9320 fiber connection to IE3300

Resolved Caveats in Cisco IOS XE 17.17.1

Identifier	Description
CSCwk80517	IE9300: TC stops forwarding PTP sync/followup messages during BMCA.
CSCwm50612	IE9300/IE3100: SNMP ifOperStatus MIB incorrectly reporting port-channel interface down
CSCwm63597	IE9320: Port LED color changed to AMBER with PRP channel shutdown/no shutdown.
CSCwm64394	IE9K cisco-ie-global macro contains commands which are not compatible with the switch.

Identifier	Description
CSCwm73744	Packet priority incorrect in TC mode.
CSCwm73805	Two GM switching is not working for announce packets with 2packets/sec and 4packets/seconds.
CSCwo25497	Two GM follow_up messages is not sending properly from IE9300.
CSCwj74266	IE9K/IE3500: Alarm relay-mode states not consistent with output alarm pins' polarity

Troubleshooting

For the most up-to-date, detailed troubleshooting information, see the Cisco TAC website at this URL:

https://www.cisco.com/en/US/support/index.html

Go to **Product Support** and select your product from the list or enter the name of your product. Look under Troubleshoot and Alerts to find information for the problem that you are experiencing.

Related Documentation

For more information about Cisco IOS XE, see the https://www.cisco.com/c/en/us/products/ios-nx-os-software/ios-xe/index.html.

For more information about Cisco Catalyst IE9300 Rugged Series Switches, see the https://www.cisco.com/c/en/us/support/switches/catalyst-ie9300-rugged-series/series.html

For more information on Cisco Validated Designs, see the https://www.cisco.com/go/designzone

To locate and download MIBs for selected platforms, Cisco IOS releases, and feature sets, use Cisco MIB Locator found at the following URL: https://www.cisco.com/go/mibs.

Communications, Services, and Additional Information

- To receive timely, relevant information from Cisco, sign up at Cisco Profile Manager.
- To get the business impact you're looking for with the technologies that matter, visit Cisco Services.
- To submit a service request, visit Cisco Support.
- To discover and browse secure, validated enterprise-class apps, products, solutions, and services, visit Cisco Marketplace.
- To obtain general networking, training, and certification titles, visit Cisco Press.
- To find warranty information for a specific product or product family, access Cisco Warranty Finder.

Documentation Feedback

To provide feedback about Cisco technical documentation, use the feedback form available in the right pane of every online document.

Cisco Support Community

Cisco Community is a forum where you can ask and answer questions, share suggestions, and collaborate with your peers and Cisco experts. Join the forum at: https://community.cisco.com/

Cisco Feature Navigator (CFN)

The Cisco Feature Navigator provides links to browse Cisco products and find relevant features and licenses. It also allows you to compare platforms, determine common features between products, and identify unique product features.

The CFN also has a tab that provides a MIB Locator.

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: https://www.cisco.com/c/en/us/about/legal/trademarks.html. Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1721R)

© 2025 Cisco Systems, Inc. All rights reserved.