排除CUBE SP拒绝转发到PSTN号码的内部呼叫故障

目录

简介
问题：从IP电话4002到4001的呼叫时主叫方听到快速忙音
解决方案
步骤1. Cisco Unified Communication Manager(CUCM)日志分析。
步骤2. CUBE SP日志分析。
步骤3.根据排除步骤1和2的故障确认其命中错误。
解决方法
应用解决方法后出现新问题
使用SIP报头编辑器解决此问题
步骤
验证
无转移报头修改
SIP听筒编辑器匹配转移报头

简介

本文档介绍当思科统一边界元素（SP版）(CUBE SP)拒绝内部呼叫时如何对其进行故障排除，内部呼叫被配置转发到PSTN号码。

呼叫流：内部IP电话4002呼叫内部IP电话4001,ip电话4001上的所有呼叫都转发到已配置的PSTN号码。

问题：从IP电话4002到4001的呼叫时主叫方听到快速忙音

主叫方使用IP电话1呼叫另一IP电话2,IP电话2配置为将所有呼叫转发到外部PSTN号码。呼叫无法连接PSTN电话，PSTN电话不振铃，呼叫者听到快速忙音。

解决方案

以下是排除故障的步骤。

步骤1. Cisco Unified Communication Manager(CUCM)日志分析。

从CUCM日志中，可以看到来自CUBE SP的错误消息。

```
SIP/2.0 604 Does Not Exist Anywhere
```

详细信息消息：

```
SIP/2.0 604 Does Not Exist Anywhere from cube SP
 82645958.001 |13:08:46.297 |AppInfo |SIPTcp - wait_SdlSPISignal: Outgoing SIP TCP message to
10.4.15.253 on port 5060 index 18491 [19580587,NET] INVITE sip:+612xxxxxxxx@10.x.x.x:5060
SIP/2.0 Via: SIP/2.0/TCP 10.4.15.5:5060;branch=z9hG4bK3cc7264a831cc4 From:
<sip:+612xxxxxxx@10.x.x.x>;tag=8162255~9cbf8c07-9c9b-758f-e658-bebd74e53d96-40280558 To:
<sip:+614xxxxxxx@10.4.15.253> Date: Fri, 17 Nov 2017 02:08:46 GMT Call-ID: 3cf99080-a0e144ae-
3692cb-50f040a@10.x.x.x Supported: 100rel,timer,resource-priority,replaces Min-SE: 1800 User-
Agent: Cisco-CUCM10.5 Allow: INVITE, OPTIONS, INFO, BYE, CANCEL, ACK, PRACK, UPDATE, REFER,
SUBSCRIBE, NOTIFY CSeq: 101 INVITE Expires: 180 Allow-Events: presence, kpml Supported: X-cisco-
srtp-fallback Supported: Geolocation Call-Info:
<sip:10.x.x.x:5060>;method="NOTIFY;Event=telephone-event;Duration=500" Call-Info: <urn:x-cisco-
remotecc:callinfo>;x-cisco-video-traffic-class=VIDEO_UNSPECIFIED Cisco-Guid: 1022988416-
0000065536-0000118822-0084870154 Session-Expires: 1800 Diversion:
```

```
P-Asserted-Identity: x <sip:+612xxxxxxxx@10.x.x.x>
Remote-Party-ID: x <sip:+612xxxxxxxx@10.x.x.x>;party=calling;screen=yes;privacy=off
```

步骤2. CUBE SP日志分析。

从CUBE SP日志中，您可以看到呼叫未通过源号码分析，因为它与任何条目都不匹配。

内部na-src-prefix-table

转移：**<sip:9180@10.x.x.x>;reason=unknown;privacy=off;screen=yes**

```
Routing fails.
SBC Index = 0X00000001
Config set Index = 0X0000270F
Source Account = CUCM-TL1
Source Adjacency = CUCM-cust01-1
Calling Address Type = 0X00030000
Called Address Type = 0X00030000
Calling Address = 9180
Called Address = +614xxxxxxxx
```

步骤3.根据排除步骤1和2的故障确认其命中错误。

这符合已知的Bug CSCup67940

CUCM需要在转接报头中发送E.164号码，以便**extend&connect**。

https://bst.cloudapps.cisco.com/bugsearch/bug/CSCup67940/?referring_site=bugquickviewredir

解决方法：

除非我们在CUBE中进行修改以接受来自转移报头的邀请，否则此邀请包含电话DN，例如**26708 <sip:26708@58.162.59.181>;reason=unknown;privacy=off;screen=yes**

解决方法

根据解决方法，允许在“转移”报头中输入号码。

这可以在此na-src-prefix-table**中添加新条目**。

```
na-src-prefix-table   xxxxx

     entry  10
     action accept
     match-prefix  9
```

应用解决方法后出现新问题

应用此工作后，呼叫成功连接，但五位分机号码将发送到服务提供商。

使用SIP报头编辑器解决此问题

在实验中测试，当您使用SIP报头编辑器修改CUBE SP中的转接报头时，它会成功连接呼叫并将e164号码发送给服务提供商。

步骤

在实验测试中，IP电话4002呼叫4001，在IP电话4001上呼叫前转到60006009(PSTN)号码。

```
sip header-editor donnietest
    store-rule entry 1
     condition header-name Diversion header-value regex-match "sip:4\(...\)" store-as
diversionuri
    header diversion entry 1
     action replace-value value
"<sip:+888888884${diversionuri}@10.66.75.51>;reason=unconditional;

privacy=off;screen=yes"
      condition header-name Diversion header-value regex-match "sip:4\(...\)@"



 adjacency sip donniecucm
    editor-type editor
    header-editor inbound donnietest
```

验证

无转移报头修改

如果不修改任何转移报头，您可以看到CUCM的邀请，转移报头位于下方

```
Diversion: <sip:4001@10.66.75.51>;reason=unconditional;privacy=off;screen=yes
INVITE sip:60006099@10.66.75.33:5068 SIP/2.0
Via: SIP/2.0/TCP 10.66.75.51:5060;branch=z9hG4bK1ef607cac8bd6
```

```
From: "agent2-4002" <sip:4002@10.66.75.51>;tag=194346~4c742393-721f-476b-82c3-bc13f8a9c6cd-
22765770
To: <sip:60006099@10.66.75.33>
Date: Sun, 19 Nov 2017 23:39:16 GMT
Call-ID: d9ad6f80-a1211624-1eee8-334b420a@10.66.75.51
Supported: timer,resource-priority,replaces
Min-SE:  1800
User-Agent: Cisco-CUCM11.5
Allow: INVITE, OPTIONS, INFO, BYE, CANCEL, ACK, PRACK, UPDATE, REFER, SUBSCRIBE, NOTIFY
CSeq: 101 INVITE
Expires: 180
Allow-Events: presence, kpml
Supported: X-cisco-srtp-fallback
Supported: Geolocation
Call-Info: <sip:10.66.75.51:5060>;method="NOTIFY;Event=telephone-event;Duration=500"
Call-Info: <urn:x-cisco-remotecc:callinfo>;x-cisco-video-traffic-class=DESKTOP
Session-ID: 223cb8ec818c0c0dd669d19baa194344;remote=00000000000000000000000000000000
Cisco-Guid: 3652022144-0000065536-0000000027-0860570122
Session-Expires:  1800
Diversion: <sip:4001@10.66.75.51>;reason=unconditional;privacy=off;screen=yes
P-Asserted-Identity: "agent2-4002" <sip:4002@10.66.75.51>
Remote-Party-ID: "agent2-4002" <sip:4002@10.66.75.51>;party=calling;screen=yes;privacy=off
Contact: <sip:4002@10.66.75.51:5060;transport=tcp>
Max-Forwards: 69
Content-Length: 0
```

SIP听筒编辑器匹配转移报头

SIP报头编辑器将Divsion Header Start与**sip:4xxx@匹配**，然后使其+E164格式

在sip报头编辑器后可以看到它。在转移报头中，4001已修改为+888888884001

转移：<sip:+888888884001@10.66.75.51>;reason=unconditional;privacy=off;screen=yes

味精 — 6401-0027-69FECA-0747于2017年11月01:48:38日(491542613毫秒
): 0X01000E2059EBD60A

模块在编辑后返回消息。
编辑器名称= donnietest
编辑器配置集= 0X00000000
这是编辑后的消息。

```
INVITE sip:60006099@10.66.75.33:5068 SIP/2.0
Supported: X-cisco-srtp-fallback
Via: SIP/2.0/TCP 10.66.75.51:5060;branch=z9hG4bK1f11c18671c97
From: "agent2-4002" <sip:4002@10.66.75.51>;tag=194931~4c742393-721f-476b-82c3-bc13f8a9c6cd-
22765859
To: <sip:60006099@10.66.75.33>
Date: Mon, 20 Nov 2017 02:13:12 GMT
Call-ID: 5ac33180-a1213a38-1f045-334b420a@10.66.75.51
Min-SE: 1800
User-Agent: Cisco-CUCM11.5
Allow: INVITE, OPTIONS, INFO, BYE, CANCEL, ACK, PRACK, UPDATE, REFER, SUBSCRIBE, NOTIFY
CSeq: 101 INVITE
Expires: 180
```

```
Allow-Events: presence, kpml
Call-Info: <sip:10.66.75.51:5060>;method="NOTIFY;Event=telephone-event;Duration=500"
Call-Info: <urn:x-cisco-remotecc:callinfo>;x-cisco-video-traffic-class=DESKTOP
Session-ID: 223cb8ec818c0c0dd669d19baa194929;remote=00000000000000000000000000000000
Cisco-Guid: 1522741632-0000065536-0000000050-0860570122
Session-Expires: 1800
Diversion: <sip:+888888884001@10.66.75.51>;reason=unconditional;privacy=off;screen=yes
P-Asserted-Identity: "agent2-4002" <sip:4002@10.66.75.51>

Remote-Party-ID: "agent2-4002" <sip:4002@10.66.75.51>;party=calling;screen=yes;privacy=off
Contact: <sip:4002@10.66.75.51:5060;transport=tcp>
Max-Forwards: 69
Content-Length: 0
```

味精 — 6401-0028-69FECA-0885于2017年11月01:48:38日(491542613毫秒): 0X01000E2059EBD60A

对邮件进行编辑。

这是编辑后的消息

```
INVITE sip:60006099@10.66.75.33:5068 SIP/2.0
Supported: X-cisco-srtp-fallback
Via: SIP/2.0/TCP 10.66.75.51:5060;branch=z9hG4bK1f11c18671c97
From: "agent2-4002" <sip:4002@10.66.75.51>;tag=194931~4c742393-721f-476b-82c3-bc13f8a9c6cd-
22765859
To: <sip:60006099@10.66.75.33>
Date: Mon, 20 Nov 2017 02:13:12 GMT
Call-ID: 5ac33180-a1213a38-1f045-334b420a@10.66.75.51
Min-SE: 1800
User-Agent: Cisco-CUCM11.5
Allow: INVITE, OPTIONS, INFO, BYE, CANCEL, ACK, PRACK, UPDATE, REFER, SUBSCRIBE, NOTIFY
CSeq: 101 INVITE
Expires: 180
Allow-Events: presence, kpml
Call-Info: <sip:10.66.75.51:5060>;method="NOTIFY;Event=telephone-event;Duration=500"
Call-Info: <urn:x-cisco-remotecc:callinfo>;x-cisco-video-traffic-class=DESKTOP
Session-ID: 223cb8ec818c0c0dd669d19baa194929;remote=00000000000000000000000000000000
Cisco-Guid: 1522741632-0000065536-0000000050-0860570122
Session-Expires: 1800
Diversion: <sip:+888888884001@10.66.75.51>;reason=unconditional;privacy=off;screen=yes
P-Asserted-Identity: "agent2-4002" <sip:4002@10.66.75.51>
Remote-Party-ID: "agent2-4002" <sip:4002@10.66.75.51>;party=calling;screen=yes;privacy=off
Contact: <sip:4002@10.66.75.51:5060;transport=tcp>
Max-Forwards: 69
Content-Length: 0
```

关于此翻译
思科采用人工翻译与机器翻译相结合的方式将此文档翻译成不同语言，希望全球的用户都能通过各自的语言得到支持性的内容。

请注意：即使是最好的机器翻译，其准确度也不及专业翻译人员的水平。

Cisco Systems, Inc. 对于翻译的准确性不承担任何责任，并建议您总是参考英文原始文档（已提供链接）。