

No IMSI or MSISDN Included in LRR for VoLTE EM Call from User of Foreign Network

- Feature Summary and Revision History, on page 1
- Feature Changes, on page 2
- Command Changes, on page 2

Feature Summary and Revision History

Summary Data

Applicable Product(s) or Functional Area	MME
Applicable Platform(s)	• ASR 5500 • VPC-DI
Feature Default	Disabled - Configuration Required
Related Changes in This Release	Not Applicable
Related Documentation	• *Command Line Interface Reference* • *MME Administration Guide*

Revision History

Revision Details	Release
Unauthorized IMSI is sent in the LRR message using the CLI.	• 21.27 • 21.26 • 21.25.6

Feature Changes

Previous Behavior: Unauthorized International Mobile Subscriber Identity (IMSI) is not sent in the LRR message.

New Behavior: The **unauth-imsi** CLI allows MME to send unauthorized IMSI in the LRR message when available.

Command Changes

Use the following configuration to enable unauthorized IMSI in the LRR message.

```
configure
  context context_name
    location-service service_name
      slr emergency unauth-imsi
      end
```

NOTES:

- **slr emergency unauth-imsi**: Allows MME to send unauthorized IMSI in the LRR message when available.